



**The article is no longer in our assortment.**

---

**Features:****OMNITRONIC PM-444USB 4-Channel DJ mixer**

4-channel DJ mixer with USB interface

- Built-in USB audio interface allows recordings and playback of digital audio files with a computer (PC and Mac)
- Full duplex USB port allows simultaneous recording and playback
- 4 channels with gain control, 2-band equalizer, cue button and channel fader
- 1 DJ microphone channel with talkover selector and 2-band equalizer
- Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
- Replaceable crossfader for crossfading between input channels with assignment switches
- Master channel with level control and 6-digit stereo LED level meter
- Outputs: master (stereo XLR/RCA), record (stereo RCA), headphones (6.3 mm jack)
- The device can be connected via USB to the PC
- (19") 48.3 cm rack installation 4 U

**Package contents**

- 1 x mixer, 1 x user manual, 1 x power cord, 1 x uSB cable

**ROADINGER Mixer Case Pro MCB-19, sloping, bk, 6U**

Rack case

- Upward tilted profile rails for top-operated units
- High-quality workmanship with plywood multi-layer glued 7 mm, black, laminated
- Interior with foam padding
- Removable cover
- Aluminum profile frames 25mm with rounded edges

---

**Logistic**

- Rugged carrying handle
- 2 high-quality butterfly locks with shut-off function
- Rubber feet
- With profile rails suitable for 19" units
- 6 U
- For further information about this product, please refer to the Data Sheet under "Downloads"

## Technical specifications:

---

Weight: 9,20 kg

---

### OMNITRONIC PM-444USB 4-Channel DJ mixer

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	25,00 W
Protection class:	Protection class II
Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Frequency range:	20 - 20000 Hz
S/N ratio:	>60 dB
Impedance:	Input: Microphone 1 kOhm Input: line 1 kOhm Input: phono 1 kOhm
Gain:	Input: variable
Control elements:	Crossfader selector switch, Crossfader, source selector, power switch
Status LED:	Power, CUE, master level meter, chanal level meter
Connections:	Input: Microphone via 1 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version) Input: line via 5 x stereo RCA Input: phono via 2 x stereo RCA Output: master via 2 x 3-pin XLR Output: master via 1 x stereo RCA Output: rec. via 1 x stereo RCA Output: rec. via 1 x USB B (F) mounting version Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
Channels:	Input channel: 2 x stereo with line-phono switch via RCA, channel control via fader, 2-band tone control EQ -30dB to 12dB at 80Hz/12kHz, gain control  Input channel: 1 x stereo with Line-line switch via RCA, channel control via fader, 2-band tone control EQ -30dB to 12dB at 80Hz/12kHz, gain control, CUE switch  Input channel: 1 x stereo with Line-USB switch via RCA or USB, channel control via fader, 2-band tone control EQ -30dB to 12dB at 80Hz/12kHz, gain control

Microphon chanal: 1 x mono via Combination socket (XLR/jack), channel control via Rotary dial, 2-band tone control EQ -30dB to12dB at 70Hz/13kHz, Cue-mix-function

Master output: 1 x stereo via XLR or RCA, channel control via Rotary dial

Headphones output: stereo via Jack, channel control via Rotary dial

---

USB port:	USB 2.0, Typ B
PC connect:	Via USB
Housing design:	(19") 48.3 cm rack installation 4 U
Dimensions:	Width: 48,3 cm Depth: 17,8 cm Height: 8,9 cm
Weight:	2,90 kg

---

#### **ROADINGER Mixer Case Pro MCB-19, sloping, bk, 6U**

Maximum load:	25 kg
Removable covers:	1 pc/pcs
Aluminum profile frames:	25 mm
Carrying handle:	1 pc/pcs
Lock:	Butterfly lock: 2 pc/pcs with shut-off function
Transport aid:	Rubber feet
Material:	Plywood multi-layer glued, 7 mm
Color:	Black, laminated
Inside dimensions:	31 cm x 10 cm
Front panel width:	19"
Mounting height:	Approx. 26.5 cm (6 U)
Mounting depth:	100 mm - 180 mm
Housing design:	6 U
Dimensions:	Width: 54,5 cm Depth: 35 cm Height: 24 cm
Weight:	6,30 kg

---