

OMNITRONIC PM-322 DJ mixer

PRO 2+1-channel DJ mixer

Art. No.: 10006816

GTIN: 4026397193459



The article is no longer in our assortment.

Features:

- 2 input channels, switchable phone/line with 3-way equalizer
- 1 separate DJ mic channel with input sensitivity control (gain), 2-fold tone control (bass, treble) and talkover selector
- Microphone input via 6.3 mm mono jack on the faceplate
- High-quality and super-smooth channel faders
- Super-smooth crossfader replaceable from above
- Headphones output adjustable via Cue Level control
- Additional Cue Split/Cue Mix switch
- Cue Split function: the Cue signal is on the one side of the headphones and the output signal on the other side
- Cue Mix function: the adjustable mix of Cue signal and output signal is on both sides of the headphones
- Mixing of the headphones signal possible via cue mixing fader
- Master out 10-fold LED level displays (L/R)
- Master control
- Rec Out independent from Master level for records with static level

Logistic

EAN / GTIN: 4026397193459

Weight: 2,50 kg

Length: 0.27 m

Width: 0.13 m

Height: 0.34 m

Technical specifications:

Power consumption:	4,50 W
Frequency range:	20 - 20000 Hz
Dimensions:	Width: 17,8 cm Depth: 27 cm

	Height: 8,5 cm
Weight:	2,05 kg
Power supply:	230 V AC, 50 Hz,
	via supplied power unit
Inputs:	2 phono, 4 line, 1 mic
Minimum input voltage:	
Microphone:	2 mV, 4 kohms
Phono:	3 mV, 50 kohms
Line:	200 mV, 6 kohms
Output voltage:	4.5 V peak to peak
Outputs:	1 master, 1 rec via RCA
Distortion:	<0.09 %
S/N ratio:	60 dB
Talkover attenuation:	-14 dB