

## OMNITRONIC PM-3010B Pro DJ mixer

PRO 3+1-channel DJ mixer with matrix

Art. No.: 10006851

GTIN: 4026397313055



**The article is no longer in our assortment.**

### Features:

- Matrix input assignment: each channel with routing facility of all input sources as desired
- 3 channels with gain control, 3-band equalizer, cue button, smooth and durable fader and 10-digit LED level meter
- 1 DJ microphone channel with 3-band equalizer, level control, on air and talkover selector
- Color illuminated rotary controls and rubber buttons
- Prefader listening to all input channels and the master output via adjustable headphones output, with cue mix/split function
- Replaceable crossfader with VCA technology for crossfading between input channels, with assignment switches, adjustable curve and reverse function
- Master control and stereo LED level meter
- Master level switchable 0.75 V or 1.5 V
- Separately controllable monitor and zone outputs
- Separately controllable session output to connect a further mixer
- 2 recording outputs, independent of the master and with on/off switch for DJ microphone signals
- Inputs: 4 x line (stereo RCA); 3 x phono/line (stereo RCA), switchable; 1 x DJ microphone (XLR/6.3 mm jack), 2 x microphone (6.3 mm jack) and 1 x headphones (6.3 mm jack)
- Outputs: 1 x master (stereo XLR/stereo RCA), 1 x zone (6.3 mm stereo jack, bal.), 1 x booth (stereo RCA), 2 x record (stereo RCA) and 1 x session (stereo RCA)
- Operation via supplied power unit

### Logistic

EAN / GTIN: 4026397313055

Weight: 5,00 kg

Length: 0.47 m

Width: 0.28 m

Height: 0.17 m

### Technical specifications:

Power consumption: 35,00 W

Frequency range: 20 - 20000 Hz

Dimensions:	Width: 34 cm Depth: 22 cm Height: 11 cm
Weight:	4,55 kg
Power supply:	230 V AC, 50 Hz, via supplied power unit
Inputs:	
DJ microphone:	combined XLR/6.3 mm jack (1/4") (bal.)
MIC 1, 2:	6.3 mm jack (1/4") (bal.)
Minimum input voltage:	1 mV RMS
LINE/PHONO 1-3:	stereo RCA
Minimum input voltage:	150 mV RMS (line), 3 mV RMS (phono)
AUX 1-4:	stereo RCA
Minimum input voltage:	150 mV RMS
Outputs:	
MASTER:	stereo XLR/stereo RCA
Output voltage:	0.75 V/1.5 V RMS (switchable)
ZONE:	6.3 mm stereo jack
Output voltage:	0.75 V RMS
BOOTH:	stereo RCA
Output voltage:	0.75 V RMS
REC:	stereo RCA
Output voltage:	0.75 V RMS
Headphones output:	6.3 mm jack (min. 8 ohms)
Tone control (DJ microphone):	
1 x high:	-12 dB to +12 dB/ 10 kHz, $\pm 1$ dB
1 x middle:	-12 dB to +12 dB/ 1 kHz, $\pm 1$ dB
1 x low:	-12 dB to +12 dB/ 100 Hz, $\pm 1$ dB
Talkover attenuation:	-15 dB
Tone control (channel 1-3):	
3 x high:	-26 dB to +12 dB/ 10 kHz, $\pm 1$ dB
3 x middle:	-26 dB to +12 dB/ 1 kHz, $\pm 1$ dB
3 x low:	-26 dB to +12 dB/ 100 Hz, $\pm 1$ dB
S/N ratio:	>75 dB
Distortion:	0.03%
Dimensions (WxHxD):	340 x 220 x 110 mm