

OMNITRONIC EM-260B Entertainment Mixer

6-channel microphone/line mixer

Art. No.: 10007076

GTIN: 4026397357981



List price: 236.81 €

incl. 19% VAT.

Description:

Mixer for microphone and line sources

The perfect tool for your karaoke party: With the Omnitronic EM-260B Entertainment Mixer you mix 3 microphone and 3 line sources to one stereo output - in a very simple way. Installing the mixer is easy as well, thanks to the small dimensions you are flexible.

Design clearly arranged

Even if you are a beginner, you can operate the mixer very easily. As it is clearly structured, you won't get lost. Each channel has a clip LED. The microphone inputs show optional 12 V phantom power. The unit is perfectly suited for bar, restaurant or club house installation.

Effects an recording sessions

With the FX send/return (with FX level control) you can cut in effects to support your voice. Record singing sessions by using the record output.

Features:

- 6 inputs (3 x mic/line and 3 x line) for mixing to 1 stereo output
- Ideal e.g. for karaoke when microphones need to mixed with CDs
- 3 mono input channels mic/line (XLR, bal.), switchable
- 3 stereo line input channels (RCA)
- Clip LED for each microphone channel
- Each microphone input with optional 12 V phantom power
- FX send/return with FX level control
- Stereo master out (6.3 mm jack) with 2-band equalizer (highs and lows) and level control

Logistic

EAN / GTIN: 4026397357981

Weight: 2,65 kg

Length: 0.54 m

Width: 0.27 m

Height: 0.09 m

- Stereo record output (RCA)
- (19") 48.3 cm rack installation 1 U
- For application areas such as: Installation; restaurants, bars and hotels; Clubs/dancing school

Package contents

- 1 x device, 1 x power cord, 1 x user manual

Technical specifications:

| | |
|--------------------|--|
| Power supply: | 115/230 V AC, 50/60 Hz |
| Power consumption: | 5 W |
| Protection class: | Protection class I |
| Power connection: | Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided) |
| Frequency range: | 20 - 20000 Hz |
| Phantom power: | Or 12 V DC |
| Housing color: | Black |
| Control elements: | Phantom power switch, power switch, FX send/return control |
| Status LED: | Power, clip |
| Connections: | Input: mic/line via 3 x 3-pin XLR Input: line via 3 x stereo RCA Input: FX via 2 x 6.3 mm jack socket (mono) mounting version Output: rec. via 1 x stereo RCA Output: master via 2 x 6.3 mm jack socket (mono) mounting version Output: FX via 1 x 6.3 mm jack socket (stereo) mounting version |
| Channels: | Input channel: 3 x stereo via RCA, channel control via Rotary dial, 2-band tone control EQ 100Hz/10kHz Microphon channel: 3 x mono with Mic-line switch via XLR, channel control via Rotary dial Master output: 1 x stereo via Jack, channel control via Rotary dial |
| Max. level: | Input: Microphone +14 dB Input: line +24 dB |
| Material: | Metal |
| Housing design: | (19") 48.3 cm rack installation 1 U |
| Dimensions: | Width: 48,3 cm Depth: 12,3 cm Height: 4,45 cm |
| Weight: | 2,30 kg |