

## OMNITRONIC CS-408 Powered Mixer

Universal powered stage mixer with 8 channels, 2 x 200 W/4 ohms

Art. No.: 10050050

GTIN: 4026397183283



**The article is no longer in our assortment.**

### Features:

- Low-noise 8-channel mic/line mixer and amplifier with 2 x 200 W/4 ohms output power
- Adjustable digital reverb
- 8 mono input channels (XLR and 6.3 mm jack) with gain control, 2-band EQ, pan and effect control
- Insert or direct out (6.3 mm jack) per input channel
- Aux send per channel for controlling external effectors
- Adjustable effect way for controlling external effect units (aux send/return)
- Tape input and output, switchable (stereo RCA)
- Adjustable headphones output (6.3 mm jack)
- +48V phantom power, can be switched centrally
- 2 x 7-band graphic equalizer for fine-tuned sound
- Precise 5-fold stereo LED meter
- 2 Speaker outputs
- Digital signal processor

### Logistic

EAN / GTIN: 4026397183283

Weight: 11,10 kg

Length: 0.35 m

Width: 0.35 m

Height: 0.54 m

### Technical specifications:

Power supply: 115/230 V AC, 50/60 Hz

Power consumption: 800,00 W

Output power: Max. 400 W

200 W RMS (4 ohms)

Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)
Frequency range:	10 - 60000 Hz Microphone 10 - 60000 Hz mono 10 - 55000 Hz stereo
S/N ratio:	>112 dB
THD:	<0,01 % at 1 kHz
DSP:	Digital signal processor
Circuitry:	Class AB
Equalizer:	Master: 2 x Graphic equalizer 7-band
Dimensions:	Width: 44 cm Depth: 26 cm Height: 27,5 cm
Weight:	9,20 kg
Inputs:	
8 mono	XLR or balanced 6.3 mm jacks
1 Aux Return:	balanced 6.3 mm jack
1 Tape In	stereo RCA
Outputs:	
1 Main Out:	Speaker sockets
1 Headphones	balanced 6.3 mm jack
1 Aux Send:	balanced 6.3 mm jack
1 Tape Out	RCA
Tone control/channel:	
Treble:	$\pm 15$ dB at 12 kHz
Middle:	$\pm 15$ dB at 2.5 kHz
Bass:	$\pm 15$ dB at 80 Hz
Power output sine:	
Stereo 4 ohms	2 x 200 W