

## OMNITRONIC LS-1222A Powered Live Mixer

12-channel live mixer with 2 x 300 W/4 ohms

Art. No.: 10060200

GTIN: 4026397206562



**The article is no longer in our assortment.**

### Features:

- Low noise 12-channel mic/line mixer
- 8 mono inputs with XLR sockets, +48V phantom power and balanced line inputs
- Insert or Direct Out for every mono channel
- 2 stereo inputs via balanced jacks
- Echo effect
- 4-band EQ for all inputs
- Peak LED per input
- 2 Aux Send (1 pre, 1 post) per channel for controlling the effects and for monitoring
- 2 mono Aux Return with balanced 6.3 mm jack sockets
- Separate Main Mix, Group and headphones outputs
- Tape inputs and outputs
- 7-band equalizer for fine-tuned sound
- Precise 10-digit LED meter
- Output power 2 x 300 W/4 ohms
- Digital signal processor
- For further information about this product, please refer to the Data Sheet under "Downloads"

### Logistic

EAN / GTIN: 4026397206562

Weight: 14,30 kg

Length: 0.59 m

Width: 0.47 m

Height: 0.24 m

### Technical specifications:

Power supply: 115/230 V AC, 50/60 Hz

Power consumption: 800,00 W

Output power: Max. 600 W  
300 W RMS (4 ohms)

Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)
Frequency range:	10 - 60000 Hz Microphone 10 - 60000 Hz mono 10 - 55000 Hz stereo
S/N ratio:	>112 dB
THD:	<0,01 % at 1 kHz
DSP:	Digital signal processor
Circuitry:	Class AB
Equalizer:	Master: 1 x Graphic equalizer 7-band stereo
Dimensions:	Width: 55 cm Depth: 39 cm Height: 12,5 cm
Weight:	12,25 kg
Inputs:	
8 mono	XLR or balanced 6.3 mm jacks
8 inserts	6.3 mm jacks
2 stereo	balanced 6.3 mm jacks
1 Aux Return:	balanced 6.3 mm jack
Tape In	RCA
Outputs:	
1 Main Out:	XLR or balanced 6.3 mm jacks
1 Headphone	balanced 6.3 mm jack
1 Aux Send:	balanced 6.3 mm jack
8 Direct Out	6.3 mm jacks
Tape Out	RCA
Tone control/channel:	
Treble:	±15 dB at 12 kHz
Middle:	±15 dB at 2.5 kHz
Bass:	±15 dB at 80 Hz
Power output sine:	
Stereo 4 ohms	2 x 300 W