

OMNITRONIC TM-105 Transmitter set W05

Multifrequency transmitter for the WAMS-05

Art. No.: 13075003

GTIN: 4026397282610



The article is no longer in our assortment.

Description:

The set includes a pocket transmitter with PLL multifrequency transmitter and a headset microphone which serves for wireless transmission of speech and vocals to the receiving unit RM-105 of the PA system W.A.M.S.-05. The transmitter operates in the range of 863.100 - 864.900 MHz. The frequency range is divided into 16 channels, which can be selected as desired. The unit is tuned to the frequencies of the receiver module.

Logistic

EAN / GTIN: 4026397282610

Weight: 0,23 kg

Length: 0.17 m

Width: 0.13 m

Height: 0.06 m

Features:

- Set includes pocket transmitter and headset microphone
- Transmitter as UHF PLL system, suitable for W.A.M.S.-05 system
- Suitable for optional lavalier microphone LS-105
- Operation in the low-interference UHF-band (863.1-864.9 MHz) with 16 frequencies selectable
- LCD for channel, frequency and battery capacity
- Sensitivity adjustable in 3 steps
- Transmitting power 10 mW
- For 2 x 1.5 V mignon batteries or 2 x 1.2 V rechargeable batteries (type AA) (not included)
- With charging contacts, suitable for optional charging station TM-105
- Connection via 3.5 mm mini jack
- License-free and approved in the EU

Technical specifications:

Battery:	2 x Mignon (AA) (not included)
Frequency band:	UHF

Dimensions:	Width: 8,8 cm Depth: 6,4 cm Height: 2,6 cm
Weight:	170 g
Modulation:	FM
Carrier frequency:	UHF 863.000-865.000 MHz
Microphone type:	Condenser with cardioid pattern
RF power output:	10 mW
Coverage:	50-70 m (with line-of-sight)
Frequency range:	50-18000 Hz (± 3 dB)
Frequency stability:	± 0.005 %
Rechargeable battery life:	approx. 11 hours
Audio input:	3.5 mm stereo mini jack