



The article is no longer in our assortment.

Features:

EUROLITE LED KLS-2500 Compact-Light-Set

Bar with 4 spots with 7 x 10 W 5in1 LED each, with 5-pin QuickDMX connector

- Complete LED light set with four slimline LED spots
- Crossbar with integrated DMX control unit
- Installation via TV pin for tripods with 28 mm interior diameter
- Ultra-light ideally suited for mobile use
- 7 PCL LEDs (RGBAW) per spot
- Comes pre-assembled with practical transport bag
- Movable and tiltable spotlights
- Sound-control via built-in microphone with sensitivity control
- DMX-controlled operation or stand-alone operation with processor-controlled color change
- Supports QuickDMX - the wireless DMX-system from Eurolite
- Built-in phantom fed socket for QuickDMX receiver (see accessories)
- Master/Slave operation
- Sound-control via built-in microphone with sensitivity control
- Convenient control possible via optional foot pedal FP-1
- DMX512 control via regular DMX controller (occupies 28 channels)
- Via DMX, each spot can be individually controlled
- DMX functions: dimmer, automatic mode, music control, strobe effect
- Addressing and setting via control panel with OLED display
- Suited for installation on a lighting stand (not included) or truss
- Black lacquered metal version
- Ideal for bands, stages or solo entertainers
- Ready for connection with power cord and PowerCon input
- 4 IEC outputs for power supply of further devices

Logistic

- 7 powerful LEDs 10 W high-power 5in1 PCL RGBWA (homogenous color mix)
 spots controlled separately
- The device is cooled by passive convection cooling
- Control via stand-alone; DMX; foot switch (optional)
- Preprogrammed in Light´J; LED PC-Control 512; EASY SHOW 1; Light Captain
- With a beam angle of 17,4°

Package contents

- 1 x spotlight

EUROLITE QuickDMX Wireless Transmitter

Compact wireless DMX transmitter 2.4 GHz

- User-friendly 3-pin XLR adapter (male) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Can transmit up to 512 DMX channels
- Control via QuickDMX; DMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity, 1 x external mains adapter, 1 x USB cable

EUROLITE QuickDMX Wireless receiver phantom-power

Compact wireless DMX receiver 2.4 GHz, phantom powered

- User-friendly 5-pin XLR adapter(female) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Requires 5 V phantom power for operation
- Can receive and process up to 512 DMX channels
- Control via DMX; QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity

Technical specifications:

| | |
|---------|----------|
| Weight: | 15,94 kg |
|---------|----------|

EUROLITE LED KLS-2500 Compact-Light-Set

| | |
|---------------|------------------------|
| Power supply: | 100-240 V AC, 50/60 Hz |
|---------------|------------------------|

| | |
|--------------------|----------|
| Power consumption: | 190,00 W |
|--------------------|----------|

| | |
|--------------------|------|
| IP classification: | IP20 |
|--------------------|------|

| | |
|-------------------------|---|
| Power connection: | Mains input via PowerCON (blue), mounting version power supply cord with safety plug (provided) |
| Power output: | 1 x PowerCON (gray), mounting version |
| Lamp type: | LED lamp |
| LED type: | 7 x 10 W high-power 5in1 PCL RGBWA (homogenous color mix) |
| DMX channels: | 2; 3; 4; 7; 20; 23; 28 |
| Cooling: | Passive convection cooling |
| Control: | Stand-alone; DMX; foot switch (optional) |
| Preprogrammed in: | Light'J; LED PC-Control 512; EASY SHOW 1; Light Captain |
| Beam angle: | 17,4° |
| Beam angle (1/2 peak): | 17,4° |
| Beam angle (1/10 peak): | 30,4° |
| Housing color: | Black |
| Dimensions: | Width: 120 cm Depth: 6 cm Height: 32 cm |
| Weight: | 15,70 kg |
| DMX channels: | 2/3/4/7/20/23/28 |
| DMX connection: | 3-pin XLR |
| QuickDMX connection: | 5-pin XLR |
| Sound-control: | via built-in microphone |
| LED type: | 10 W RGBAW (5in1) |
| Number of LEDs: | 28 |
| Beam angle: | 28° |
| TV spigot: | D = 28 mm |
| Dimensions (L x W x H): | 1160 x 60 x 320 mm |
| Special product: | Not designed for household room illumination |
| Intended use: | Show effect lighting |

EUROLITE QuickDMX Wireless Transmitter

| | |
|--------------------|--|
| Power supply: | 100-240 V AC, 50/60 Hz 5V DC 1000 mA |
| IP classification: | IP20 |
| Power connection: | Mains input via coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided) |
| DMX channels: | Output 512 |
| DMX input: | 1 x 3-pin XLR (M) |
| Control: | QuickDMX; DMX; plug and play |
| Range: | Range up to 400m |
| Carrier frequency: | 2,4 GHz |
| Parallel mode: | Max. 6 transmitter |
| RF power output: | 19 dBm |

| | |
|-------------|---------------------------------------|
| Modulation: | GFSK |
| Color: | Silver |
| Dimensions: | Length: 21,2 cm Diameter: Ø 1,8 cm |
| Weight: | 0,15 kg |

EUROLITE QuickDMX Wireless receiver phantom-power

| | |
|--------------------|---|
| Power supply: | 5V DC |
| IP classification: | IP20 |
| Power connection: | Mains input via 5-pin XLR (W) connector |
| DMX channels: | Input 512 |
| DMX output: | 1 x 5-pin XLR (F) |
| Control: | DMX; QuickDMX; plug and play |
| Range: | Range up to 400m |
| Carrier frequency: | 2,4 GHz |
| Parallel mode: | Max. 6 transmitter |
| Modulation: | GFSK |
| Color: | Silver |
| Dimensions: | Length: 21,2 cm Diameter: Ø 1,8 cm |
| Weight: | 0,10 kg |