

FUTURELIGHT WDR-1 wireless DMX receiver

Receiver for wireless data transmission

Art. No.: 51834016

GTIN: 4026397236828



The article is no longer in our assortment.

Features:

- Wireless DMX is a technology to control many DMX-devices without any cables or to bridge a distance between sender and receiver
- W-DMX is interference-free from other wireless devices in the 2.45 GHz band such as W-LAN
- W-DMX uses adaptive FHSS (Frequency Hopping Spread Spectrum) and TDMA (Time Division Multiple Access)
- One WDR-1 supports a single DMX512 universe with 512 DMX-channels
- Larger systems can easily be adapted to support up to 8,192 DMX channels (16 DMX512 universes)
- Up to 8,192 receivers can be used in a W-DMX system
- Truss installation via Omega Clamp included in the delivery

Logistic

EAN / GTIN: 4026397236828

Weight: 1,15 kg

Length: 0.21 m

Width: 0.11 m

Height: 0.29 m

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	3,00 W
Dimensions:	Width: 16,5 cm Depth: 4 cm Height: 13,5 cm
	via 6-12 V DC, 1 A power unit included in the delivery
Number of control channels:	512 (1 DMX512 universe)
Max. number of receivers:	8,192

DMX512 output:	5-pin and 3-pin XLR
Frequency:	2.450 GHz
Coverage:	1000 m (with line-of-sight)
Dimensions (L x W x H):	135 x 165 x 40 mm
Weight:	1 kg