

## OMNITRONIC CPE-120P PA Mixing Amplifier

PA mixing amplifier with audio player, IR remote control and Bluetooth, 120 W RMS

Art. No.: 80709607

GTIN: 4026397683172



**List price: 284.41 €**

incl. 19% VAT.

### Features:

- SD card slot and USB port
- FM tuner with auto scan
- 3 microphone inputs with separate level controls
- Mic 1 with phantom power and priority circuit
- Mic 2 and 3 switchable mic/line
- 2 line inputs with separate level controls
- 1 line output
- Treble and bass and master controls for the output signal
- 4-digit LED level meter
- Mains operation and 24 V emergency power operation
- The device is cooled by cooling fan
- Control via Bluetooth; IR remote control
- 2 U
- Desktop console housing
- For application areas such as: Installation; restaurants, bars and hotels; sports centres/gyms

### Logistic

EAN / GTIN: 4026397683172

Weight: 4,00 kg

Length: 0.35 m

Width: 0.27 m

Height: 0.14 m

### Package contents

- 1 x amplifier, 1 x user manual, 1 x declaration of conformity, 1 x power cord, 1 x antenna, 1 x remote control, 1 x battery

### Technical specifications:

Power supply: 230 V AC, 50 Hz  
Or  
24 V

Power consumption:	240 W
Output power:	120 W RMS
Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)
Cooling:	Cooling fan
Impedance:	4-16 ohms; Public address systems 100V; Public address systems 70V
Control:	Bluetooth; IR remote control
Audio player:	USB + SD + Bluetooth + FM Radio
Circuitry:	Class D
Controls:	Overload; short-circuit; limiter; overheat
Connections:	Input: Microphone via 1 x 3-pin XLR Input: mic/line via 2 x 6.3 mm jack socket (stereo) mounting version Input: line via 2 x stereo RCA Output: line via 1 x stereo RCA 0,774 V Output: speaker via screw terminal
Equalizer:	Master: 1 x 2-band tone control
Music format:	MP3
Housing design:	2 U Desktop console housing
Dimensions:	Width: 30,3 cm Depth: 22 cm Height: 9,1 cm
Weight:	3,70 kg
Remote control	
Battery:	1 x Button cell 3.0 V CR2025 lithium manganese built-in