

OMNITRONIC SD-28 Signal Distributor

Répartiteur de signaux à 8 voies

Réf. : 10355735

GTIN: 4026397439359



L'article n'est plus disponible.

Description:

This little and maybe even a bit mousy looking box, which demands one height unit only, is truly an effective signal distributor, which splits 2 input signals to 4 in stereo mode and spreads 1 input signal to 8 exits in mono mode. As the SD-28 is intended to be used for permanent installation, the particular level regulator has been recessed, to avoid a deliberate or accidental change of settings. The tuning of channels is, by the way, supported by clear LED-meters and therefore facilitated. Additionally, another SD-28 can be connected to improve its field of application. This system control distributor is best used for club installments or for multi stacked amplifiers.

Logistique

EAN / GTIN: 4026397439359

Poids: 2,40 kg

Longueur: 0.54 m

Largeur: 0.25 m

Hauteur: 0.09 m

Caractéristiques:

- Dedicated 2-channel signal distributor with selectable operating mode
- Stereo mode: 2 line input signals to 4 outputs each
- Mono mode: 1 line input signal to 8 outputs
- Each input with 1 parallel output for feeding through the input signal
- Each output with recessed level control (avoids unintended adjustments)
- Precise 7-digit LED meters with clip LED for input level
- Inputs and outputs via balanced XLR connectors
- Rack installation, 1 U
- (19") 48,3 cm installation en rack 1 HE

Données techniques:

Alimentation électrique: 230 V AC, 50 Hz

Puissance totale de raccordement:	10,00 W
Branchement électrique:	Alimentation électrique via Appareils froids (M) version encastrable Câble d'alimentation à prise contact de protection (inclus dans la livraison)
Plage de fréquence:	20 - 20000 Hz
Conception du boîtier:	(19") 48,3 cm installation en rack 1 HE
Dimension:	Largeur : 48,3 cm Profondeur : 12 cm Hauteur : 4,45 cm
Poids:	2,05 kg
S/N ratio:	>90 dB
THD:	0.05 %
Crosstalk:	>80 dB, -3 dB
Gain:	-- to +6 dB
Input impedance:	20 kohms
Output impedance:	150 ohms
Connection:	3-pin XLR (bal.)