

OMNITRONIC HDA-6.5 Amplifier

Amplificateur de puissance à 3 canaux 2 x 500 W + 900 W @ 4 ohms

Réf. : 10452360

GTIN: 4026397245516



L'article n'est plus disponible.

Description:

Concerning sound aspects, flexibility is the key. The HDA 6.5 amplifier can definitely be called flexible. Via two crossover networks, satellite cabinets as well as the subwoofer can be set in a way that you are able to change from background music to hot party sound with a strong base. To keep everything clean the fan grill is very helpful, as taking it down is very easy.

Caractéristiques:

- 2 x 300 W + 500 W @ 8 ohms
- 2 x 500 W + 900 W @ 4 ohms
- Low Cut switch on the rear panel
- Rotary control for adjusting the upper crossover frequency (Hi Cut) of the subwoofer
- 3 gain controls
- All operation modes controllable via LEDs, can be switched off
- Signal inputs via XLR female or terminal block
- Speaker connection via terminal block or speaker jack
- Many protection circuits for optimized equipment protection
- Forced fan cooling
- Very rugged housing
- Rack installation

Données techniques:

Alimentation électrique: 230 V AC, 50 Hz

Puissance de sortie: Max. 1900 W

Logistique

EAN / GTIN: 4026397245516

Poids: 26,50 kg

Longueur: 0.55 m

Largeur: 0.54 m

Hauteur: 0.14 m

Plage de fréquence:	20 - 20000 Hz
Dimension:	Largeur : 48,3 cm Profondeur : 45 cm Hauteur : 8,9 cm
Poids:	25 kg
Power output sine:	
Stereo 4 ohms	2 x 500 W + 900 W
Stereo 8 ohms	2 x 300 W + 500 W
Damping factor:	>250
Distortion factor:	0.05 %
Signal-to-noise ratio:	>95 dB
Min. input sensitivity:	0.775 V RMS
Input impedance:	10 kohms (unbalanced), 20 kohms (balanced)
Output impedance:	>0.02 ohms
Slew rate:	20 V/ μ sec
LED indicators (per channel):	Clip, Protect, Signal
Minimum mounting depth:	470 mm