

INTUSONIC DLA26 répartiteur de zone 2-IN-6

Séparateur stéréo 2 en 6 pour créer de grands systèmes multizones

Réf. : 12604177

GTIN: 5060502923233



Description:

The INTUWORX DLA26 is a stereo 2-in-6 splitter allowing to build large multi-zone systems fed with different levels of the same two selectable input signals. Every output/zone features a 2-band EQ, volume control and overload LED on the front panel, and can be switched to mono on the rear panel if required. Likewise, a 100Hz HPF can be engaged per zone on the rear panel, to cater for connected speaker systems potentially unable to reproduce very low frequencies. Limiting the range of the front panel volume controls, additional rear-panel controls allow to set the maximum volume for every output/zone. Aside from its splitter/zoner functions, the DLA26 also adds versatility by allowing to feed a signal from a mobile device via its front-panel 3.5mm input, and by its additional emergency features which include a mute contact and an auto-sensing emergency priority input. The DLA26 is the perfect companion to single-output mixers to build multi-zone systems.

Caractéristiques:

- Boîtier du pupitre
- Vous trouverez de plus amples informations sur ce produit dans la rubrique « Téléchargements » de la fiche technique

Données techniques:

Alimentation électrique: 115/230 V CA, 50/60 Hz

Puissance totale de raccordement: Max. 12 W

Logistique

EAN / GTIN: 5060502923233

Poids: 3,60 kg

Longueur: 0.54 m

Largeur: 0.33 m

Hauteur: 0.10 m

Branchement électrique:	Alimentation électrique via Appareils froids (M) câble d'alimentation à prise contact de protection (inclus dans la livraison)
	Tramite
Rapport signal/bruit:	>82 dB
Distorsion harmonique:	<0,06 % avec 1 kHz
Atténuation de la diaphonie:	>72 dB
Niveau max.:	Entrée: +17,8 dBU
Couleur:	Noir
Conception du boîtier:	Boîtier du pupitre
Dimension:	Largeur : 48,3 cm Profondeur : 22 cm Hauteur : 4,4 cm
Poids:	3,05 kg

Contenu de la livraison:

1 x Mode d'emploi
1 x Appareil
1 x Câble secteur/câble d'alimentation
7 x borne enfichable à vis
1 x prise
4 x pied