

## EUROLITE DMX Stage Control 136 controller

Versatile DMX controller

Réf. : 70064535

GTIN: 4026397220353



## L'article n'est plus disponible.

### Description:

Let's bring them together! On this DMX Stage control, parcans and movinglights can be operated simultaneously. It fits best in little clubs, hotel dicotheques or on manageable live events, where only a few programs are needed. The controller is easy to use and is seperated in 128 movinglight- and 8 parcan-channels.

### Caractéristiques:

- 136 control channels DMX out and MIDI in
- 8 channel-faders with LED
- Fade Time fader with LED for adjusting the step time
- Master-fader with LED for adjusting the total output level
- Speed-fader for adjusting the program-speed
- Audio-fader with LED for adjusting the music sensitivity
- CF memory card for programs
- LCD display
- External power supply
- 6.3 mm jack connection for footswitch (scene steps)
- 0/10 V-output via one 5-pin DIN-socket for fog machine
- Simultaneous and independent control of scanner and parcan section
- Dimmer: Manual control of the channels via sliders
- Full On: all channels can be switched on together
- Blackout-function
- Program speed adjustable via speed-fader or Tap Sync-button
- Sound-control via external signal or integrated microphone
- Sound to light via RCA socket
- Rack mounting plates included

### Logistique

EAN / GTIN: 4026397220353

Poids: 3,75 kg

Longueur: 0.58 m

Largeur: 0.32 m

Hauteur: 0.16 m

- Rack installation with 4 units
- Scanner Section:
  - 128 control channels for 8 scanners with up to 16 DMX channels
  - 12 pages with up to 8 scenes can be programmed
  - 8 chasers each with up to 99 steps
  - Programmable speed and fade time
  - Patch possibility
  - Joystick with fine mode and 4 step buttons
- Dimmer Section:
  - 8 dim fader channels and 1 master fader
  - 12 pages with up to 6 scenes can be programmed
  - 6 chasers each with 99 steps
  - Speed, tap-sync und audio fader
  - Step function
  - Standby and full-on
  - Peut envoyer jusqu'à 136 canaux DMX
  - Commandé via DMX
  - Boîtier du pupitre

### Données techniques:

|                                   |   |
|-----------------------------------|---|
| Alimentation électrique:          | 230 V AC, 50 Hz   |
| Puissance totale de raccordement: | 6,00 W  |
| Type de protection:               | IP20  |
| Canaux DMX:                       | Sortie 136  |
| Commande:                         | DMX   |
| Couleur:                          | Noir  |
| Conception du boîtier:            | Boîtier du pupitre  |
| Dimension:                        | Largeur : 21,5 cm<br>Profondeur : 6,4 cm<br>Hauteur : 28 cm |
| Poids:                            | 3,30 kg   |
|                                   | via 12 V DC, 600 mA power unit included in the delivery     |
| Number of control channels:       | 136   |
| Sound-control:                    | via built-in microphone or via audio-input                  |
| Audio-input:                      | Jack  |
| Audio-sensitivity:                | 0.1-1 V   |
| DMX512 output:                    | 3-pin XLR connector with polarity selector                  |
| Free chasers:                     | 8 for scanner section and 6 for dimmer section              |
| Dimensions (L x W x H):           | 483 x 180 x 93 mm   |
|                                   | Rack installation with 4 u                                  |
| Minimum mounting depth:           | 100 mm  |