

## OMNITRONIC CS-812 Powered Mixer

Universal powered stage mixer with DSP effects unit

Art.n.: 10050150

GTIN: 4026397230802



### Features :

- Low-noise 8-channel mic/line mixer and amplifier with 2 x 350 W/4 ohms output power
- Integrated DSP effect unit with LED display 256 effects
- 8 mono input channels (XLR and 6.3 mm jack) with gain control, 3-band EQ, pan and effect control
- Insert or direct out (6.3 mm jack) per channel
- Aux send per channel for controlling external effectors
- Adjustable aux return input (6.3 mm jack)
- 2 adjustable CD inputs (stereo RCA) with crossfader
- Tape output (stereo RCA)
- +48V phantom power, can be switched centrally
- 2 x 7-band graphic equalizer for fine-tuned sound
- Precise 10-fold stereo LED meter
- 2 Speaker outputs

### Logistica

EAN / GTIN: 4026397230802

Peso : 17,25 kg

Lunghezza : 0.42 m

Larghezza : 0.42 m

Altezza : 0.64 m

### Dati tecnici :

Alimentazione elettrica: 115/230 V AC, 50/60 Hz

Potenza totale installata: 1200,00 W

Potenza in uscita: Massimo 700 W

Misure: Larghezza: 54 cm

Profondità: 33 cm

Altezza: 32 cm

Peso:	14,00 kg
<b>Inputs:</b>	
8 mono	XLR or balanced 6.3 mm jacks
8 inserts	balanced 6.3 mm jacks
1 aux return	balanced 6.3 mm jacks
2 CD	RCA
<b>Outputs:</b>	
2 master	Speaker sockets
1 aux send	balanced 6.3 mm jacks
8 insert	balanced 6.3 mm jacks
1 Tape	RCA
<b>Frequency range:</b>	
Microphone:	10-60000 Hz, $\pm 3$ dB
Mono:	10-60000 Hz, $\pm 3$ dB
Stereo:	10-55000 Hz, $\pm 3$ dB
Distortion:	0.01 %
S/N-ratio:	112 dB
<b>Tone control/channel:</b>	
Treble:	$\pm 15$ dB at 12 kHz
Middle:	$\pm 15$ dB at 2.5 kHz
Bass:	$\pm 15$ dB at 80 Hz
<b>Power output sine:</b>	
Stereo 4 ohms:	2 x 350 W
Dimensions (W x D x H):	540 x 330 x 320 mm

### **Contenuto della confezione:**

---