

EUROLITE DMX Stage Control 136 controller

Versatile DMX controller

Art.n.: 70064535

GTIN: 4026397220353



Descrizione :

Let's bring them together! On this DMX Stage control, parcans and movinglights can be operated simultaneously. It fits best in little clubs, hotel dicotheques or on manageable live events, where only a few programs are needed. The controller is easy to use and is seperated in 128 movinglight- and 8 parcan-channels.

Features :

- 136 control channels DMX out and MIDI in
- 8 channel-faders with LED
- Fade Time fader with LED for adjusting the step time
- Master-fader with LED for adjusting the total output level
- Speed-fader for adjusting the program-speed
- Audio-fader with LED for adjusting the music sensitivity
- CF memory card for programs
- LCD display
- External power supply
- 6.3 mm jack connection for footswitch (scene steps)
- 0/10 V-output via one 5-pin DIN-socket for fog machine
- Simultaneous and independent control of scanner and parcan section
- Dimmer: Manual control of the channels via sliders
- Full On: all channels can be switched on together
- Blackout-function
- Program speed adjustable via speed-fader or Tap Sync-button
- Sound-control via external signal or integrated microphone
- Sound to light via RCA socket
- Rack mounting plates included

Logistica

EAN / GTIN: 4026397220353

Peso : 3,75 kg

Lunghezza : 0.58 m

Larghezza : 0.32 m

Altezza : 0.16 m

- Rack installation with 4 units
- Scanner Section:
 - 128 control channels for 8 scanners with up to 16 DMX channels
 - 12 pages with up to 8 scenes can be programmed
 - 8 chasers each with up to 99 steps
 - Programmable speed and fade time
 - Patch possibility
 - Joystick with fine mode and 4 step buttons
- Dimmer Section:
 - 8 dim fader channels and 1 master fader
 - 12 pages with up to 6 scenes can be programmed
 - 6 chasers each with 99 steps
 - Speed, tap-sync und audio fader
 - Step function
 - Standby and full-on
- Può inviare fino a 136 canali DMX
- Controllabile via DMX
- Custodia per mixer

Dati tecnici :

Alimentazione elettrica:	230 V AC, 50 Hz
Potenza totale installata:	6,00 W
Canali DMX:	Uscita 136
Attivazione:	DMX
Colore:	Nero
Struttura della custodia:	Custodia per mixer
Misure:	Larghezza: 21,5 cm Profondità: 6,4 cm Altezza: 28 cm
Peso:	3,30 kg
	via 12 V DC, 600 mA power unit included in the delivery
Number of control channels:	136
Sound-control:	via built-in microphone or via audio-input
Audio-input:	Jack
Audio-sensitivity:	0.1-1 V
DMX512 output:	3-pin XLR connector with polarity selector
Free chasers:	8 for scanner section and 6 for dimmer section
Dimensions (L x W x H):	483 x 180 x 93 mm
	Rack installation with 4 u
Minimum mounting depth:	100 mm

Contenuto della confezione: