



AC INPUT

POWER

Typ/Type: OMNITRONIC RS-1222
 Spannungsversorgung: 2 x 230 V AC
 Power supply: 50/60 Hz ~
 Gesamtanschlusswert: 25 W
 Power consumption (max.)
 OMNITRONIC SHOWEQUIPMENT GmbH, GERMANY



OMNITRONIC
 www.omnitronic.com



RECORDING MIXER

1 MIC LINE LOW CUT / 75 Hz GAIN

2 MIC LINE LOW CUT / 75 Hz GAIN

3 MIC LINE LOW CUT / 75 Hz GAIN

4 MIC LINE LOW CUT / 75 Hz GAIN

STEREO AUX RETURN L/MONO R

AUX SEND 1 2

TAPE IN TAPE OUT L R

GROUP OUT G1 G2

STEREO OUT L R

PHONES

LINE 5-6 MONO L R

LINE 7-8 MONO L R

LINE 9-10 MONO L R

LINE 11-12 MONO L R

CTRL R OUT L R

MAIN OUT L R

OMNITRONIC
RS-1222

												<p>LEVEL</p> <p>TAPE IN</p> <p>SEND 1</p> <p>SEND 2</p> <p>AUX SEND</p> <p>RETURN 1</p> <p>L-R to G1-2</p> <p>RETURN 2</p> <p>L-R to G1-2</p> <p>AUX RETURN</p> <p>G1-2 to L-R</p>	<p>+10</p> <p>+7</p> <p>+4</p> <p>+2</p> <p>0</p> <p>-2</p> <p>-4</p> <p>-7</p> <p>-10</p> <p>-20</p> <p>+48V POWER</p> <p>+48V</p> <p>HEADPHONES CTRL ROOM LEVEL</p> <p>L-R / G1-2 PFL</p> <p>G1-2 / PFL</p>
1	2	3	4	5-6	7-8	9-10	11-12	G1-2	L	R	MAIN MIX		