

OMNITRONIC MZD-88 Matrix Zone Distributor

8-channel audio mixer with 8 outputs and matrix

Art. No.: 10304120

GTIN: 4026397308389



List price: 415.31 €

incl. 19% VAT.

Description:

The OMNITRONIC MZD-88 is an audio mixer with an analog matrix of 8 input and 8 outputs which allows for multiple output configurations and inputs mixing. The 8 outputs are divided in 4 groups. Thus it's possible to supply 4 different PA zones with a stereo output by routing different input signals to these zones without having to change the cable configuration. It's also possible to obtain 8 outputs with different mixing as every input has its own level and PAN controls. Perfect for any place where multi-zone or multi-room solutions are required, just like in theme parks, conference centers, schools or as the case may be. By the way, the MZD-88 could also be used for personal monitoring.

Features:

- Matrix input assignment: 8 audio inputs are freely assignable to each of the 8 outputs
- Inputs and outputs via balanced XLR connectors
- (19") 48.3 cm rack installation 2 U
- For application areas such as: Installation; restaurants, bars and hotels; sports centres/gyms

Package contents

- 1 x device, 1 x user manual, 1 x power cord

Logistic

EAN / GTIN: 4026397308389

Weight: 4,25 kg

Length: 0.55 m

Width: 0.26 m

Height: 0.13 m

Technical specifications:

Power supply: 115/230 V AC, 50/60 Hz

Power consumption: 10,00 W

| | |
|-------------------|--|
| Power connection: | Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided) |
| Frequency range: | 20 - 20000 Hz |
| Impedance: | Input: 10 kOhm |
| Gain: | 12 dB |
| Dynamic range: | 100 dB |
| Max. level: | Input: +21 dBu |
| Housing design: | (19") 48.3 cm rack installation 2 U |
| Dimensions: | Width: 48,3 cm Depth: 19,5 cm Height: 8,9 cm |
| Weight: | 3,60 kg |