

OMNITRONIC MZD-88 Matrix Zone Distributor

8-channel audio mixer with 8 outputs and matrix

Art. No.: 10304120

GTIN: 4026397308389



Description:

The OMNITRONIC MZD-88 is an audio mixer with an analog matrix of 8 input and 8 outputs which allows for multiple output configurations and inputs mixing. The 8 outputs are divided in 4 groups. Thus it's possible to supply 4 different PA zones with a stereo output by routing different input signals to these zones without having to change the cable configuration. It's also possible to obtain 8 outputs with different mixing as every input has its own level and PAN controls. Perfect for any place where multi-zone or multi-room solutions are required, just like in theme parks, conference centers, schools or as the case may be. By the way, the MZD-88 could also be used for personal monitoring.

Features:

- Matrix input assignment: 8 audio inputs are freely assignable to each of the 8 outputs
- Inputs and outputs via balanced XLR connectors
- (19") 48.3 cm rack installation 2 U
- For application areas such as: Installation; restaurants, bars and hotels; sports centres/gyms

Logistic

EAN / GTIN: 4026397308389

Weight: 4,25 kg

Length: 0.55 m

Width: 0.26 m

Height: 0.13 m

Technical specifications:

Power supply:	115/230 V AC, 50/60 Hz
Power consumption:	10.00 W
Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)

Frequency range:	20 - 20000 Hz
Impedance:	Input: 10 kOhm
Gain:	12 dB
Dynamic range:	100 dB
Max. level:	Input: +21 dBu
Housing design:	(19") 48.3 cm rack installation 2 U
Dimensions:	Width: 48.3 cm Depth: 19.5 cm Height: 8.9 cm
Weight:	3.60 kg

Scope of delivery:

- 1 x device
- 1 x user manual
- 1 x power cord