

## OMNITRONIC LH-068 DI Box Phantom-Powered

1-channel DI box, phantom powered, active

Art. No.: 10355068

GTIN: 4026397318517



**The article is no longer in our assortment.**

### Features:

- 1 high-impedance signal input, 6.3 mm jack
- 1 low-impedance XLR output
- 6.35 mm jack input, and output
- Converts an unbalanced line input (e.g. instruments) into a balanced XLR output for connecting a mixer
- Switchable input attenuation: 0 dB, -20 dB, -40 dB
- Requires +48 V phantom power for operation
- Rugged metal housing

### Logistic

EAN / GTIN: 4026397318517

Weight: 0,46 kg

Length: 0.23 m

Width: 0.13 m

Height: 0.08 m

### Technical specifications:

Frequency range:	1 - 50000 Hz
S/N ratio:	>100 dB
Phantom power:	Or 9-48 V DC
Control elements:	Groundlift selector
Connections:	Input: 1 x 6.3 mm plug (unbal.) Output: 1 x 3-pin XLR Link: 1 x 6.3 mm plug (unbal.)
Dimensions:	Width: 9,5 cm Depth: 11,5 cm Height: 4,5 cm

Weight:

350 g

---