

## OMNITRONIC Airbros 5.8G Jack Kit

Plug-n-play wireless audio system with transmitter and receiver

Art. No.: 13072342

GTIN: 4026397686128



**The article is no longer in our assortment.**

### Description:

The new mobile freedom

Airbro offers an uninterrupted, crystal clear signal and provides a completely new experience for musicians during live performances. The easy-to-use transmitter/receiver system connects instruments to an amplifier or PA system in an uncomplicated and completely inconspicuous way. The 2-piece set frees musicians from cable restrictions and allows them to move freely on stage. The range is around 30 meters.

Clear, high-resolution sound for the entire band

Experience great sound thanks to the latest 5 GHz wireless standard and digital audio transmission over the entire frequency range with 24-bit/48 kHz resolution and an almost imperceptible delay of 5.6 milliseconds. With four selectable transmission channels, you can even assign a separate channel to each band member.

Small and rechargeable

The devices work with rechargeable lithium batteries and are housed in compact cases with folding jack plugs. Thanks to a battery life of 4 hours and more, you'll be well equipped for long gigs and rehearsals. The supplied USB charging cable comes with a practical double plug.

### Features:

#### OMNITRONIC Airbro 5.8G Jack Transmitter

Plug-n-play wireless audio transmitter

- Replaces the cable between instrument and guitar amplifier
- Enjoy freedom of movement during live performance

### Logistic

EAN / GTIN: 4026397686128

Weight: 0,25 kg

Length: 0.30 m

Width: 0.22 m

Height: 0.21 m

- Convenient and quickly ready for use thanks to one-button operation
- Operation in the interference-free 5.8 GHz band
- 24 bit/48 kHz for the ultimate sound quality
- 4 switchable transmission channels
- Several receivers can be coupled with a single transmitter
- Angle adjustable by 195°, therefore suitable for all guitar types
- Battery operation up to 4h
- Operating range up to 15m in buildings
- Operating range up to 30m in the open air
- 5.8 GHz license-free worldwide
- Up to 4 transmitters can be operated in parallel without interference
- Ultra-low latency

#### **Package contents**

- 1 x device, 1 x user manual, 1 x USB cable, 1 x screwdriver, 1 x bag

### **OMNITRONIC Airbro 5.8G Jack Receiver**

Plug-n-play wireless audio receiver

- Replaces the cable between instrument and guitar amplifier
- Enjoy freedom of movement during live performance
- Convenient and quickly ready for use thanks to one-button operation
- Operation in the interference-free 5.8 GHz band
- 24 bit/48 kHz for the ultimate sound quality
- 4 switchable transmission channels
- Several receivers can be coupled with a single transmitter
- Angle adjustable by 195°, therefore suitable for all guitar types
- Battery operation up to 4h
- Operating range up to 15m in buildings
- Operating range up to 30m in the open air
- 5.8 GHz license-free worldwide
- Up to 4 transmitters can be operated in parallel without interference
- Ultra-low latency

#### **Package contents**

- 1 x device, 1 x user manual, 1 x USB cable, 1 x screwdriver, 1 x bag

### **Technical specifications:**

Weight:	0,18 kg
---------	---------

### **OMNITRONIC Airbro 5.8G Jack Transmitter**

Type:	Transmitter
Power supply:	5V DC 1000 mA
Power connection:	Battery/battery pack
Battery pack type:	1 x lithium ion 400 mAh,
Battery pack:	Battery operation up to 4h Recharging time 2h
Frequency range:	20 - 20000 Hz
Range:	Range up to 15m in buildings Range up to 30m in the open air
Frequency band:	5.8 GHz
Parallel mode:	Max. 4 transmitter
Latency:	< 6 ms
Status LED:	Charge status indicator

Connections:	Input: 6.3 mm plug (unbal.)
Max. level:	Input: +680 mV, unbal.
USB port:	Type micro USB (F) mounting version
Dimensions:	Width: 13,8 cm Depth: 2,7 cm Height: 4,3 cm
Weight:	0,09 kg

#### OMNITRONIC Airbro 5.8G Jack Receiver

Type:	Receiver
Battery pack type:	1 x lithium ion 400 mAh,
Battery pack:	Battery operation up to 4h Recharging time 2h
Frequency range:	20 - 20000 Hz
Range:	Range up to 15m in buildings Range up to 30m in the open air
Frequency band:	5.8 GHz
Parallel mode:	Max. 4 transmitter
Latency:	< 6 ms
Status LED:	Charge status indicator
Connections:	Output: 6.3 mm plug (unbal.)
Max. level:	Output: +770 mV, unbal.
USB port:	Type micro USB (F) mounting version
Dimensions:	Width: 13,8 cm Depth: 2,7 cm Height: 4,3 cm
Weight:	0,09 kg