

OMNITRONIC Set PORTY-8A Drahtlos-PA-System + Bodypack Transmitter incl. Lavalier Mic

GTIN: 4026397739480



Features:

OMNITRONIC PORTY-8A Wireless PA System

Mobile 8" PA system with battery operation, Bluetooth, DSP and wireless microphone

- Powerful sound in an ultra-compact package (114 dB max. SPL)
- Works great as primary PA system, stage monitor and practice amp
- 4-channel mixer
- Stereo Bluetooth link for wireless stereo operation with 2 systems linked together
- UHF receiver unit and matching wireless microphone
- Lightweight plastic housing
- Cordless, flexible and versatile
- Battery operation up to 6.5h at 50% volume; battery operation up to 3.5h at 100% volume
- Integrated automatic charging of the battery and status indicator
- Digital signal processor 96kHz, 24 bit
- DSP presets: FLAT; DJ; LIVE
- Control via Bluetooth
- Bluetooth: operating range up to 20m
- UHF 863 - 865 MHz License-free and approved in Europe
- Dual flange
- Black metal grille
- With tablet holder
- Rugged carrying handle
- Application possibility: Standing; monitoring; on stand
- For application areas such as: Mobile use; mobile djs / entertainer; small rental; product presentations and lectures

Logistic

EAN / GTIN: 4026397739480

Weight: 11,00 kg

Length: 0.00 m

Width: 0.00 m

Height: 0.00 m

OMNITRONIC PORTY-8A Bodypack + Lavalier Microphone 863.1 MHz

- Operating range up to 60m
- UHF 863 - 865 MHz License-free and approved in Europe

OMNITRONIC PORTY-8A Transport Bag

- , black

Technical specifications:

Weight: 10.30 kg

OMNITRONIC PORTY-8A Wireless PA System

| | |
|------------------------|---|
| Power supply: | 100-240 V AC, 50/60 Hz |
| Power consumption: | Max. 220 W |
| Protection class: | Protection class I |
| Power connection: | Mains input via IEC connector (M) mounting version (provided) Battery/battery pack |
| Cable length: | 1.5 m detachable |
| Device fuse: | 5 x 20 mm, T 3.15 A fuse replaceable |
| Battery pack type: | 1 x lithium ion 22.2 V, 4400 mAh, 97.68 Wh |
| Battery pack: | Battery operation up to 6.5h at 50% volume Battery operation up to 3.5h at 100% volume Recharging time 4h |
| Power: | 120W RMS |
| Number of channels: | 4 |
| Frequency range: | 45 - 18000 Hz |
| Max. SPL: | 114 dB |
| DSP: | Digital signal processor 96kHz, 24 bit |
| DSP presets: | FLAT; DJ; LIVE |
| Control: | Bluetooth |
| Bluetooth: | Version: 5 with stereo link (TWS) |
| Bluetooth device name: | OMNITRONIC PORTY-8A |
| Range: | Bluetooth: range up to 20m |
| Frequency band: | UHF 863 - 865 MHz |
| Housing color: | Black |
| Attachment system: | Dual flange: Ø 35mm |
| Circuitry: | Class D |
| Control elements: | Power switch, Input sensitivity switch, Master control, level control per channel, echo effect control; connect |

| | |
|------------------|---|
| Connections: | Input: mic/line via 3 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version) Input: line via RCA (F) mounting version Input: line via 3.5 mm jack (stereo) mounting version Output: line via 3-pin XLR (M) mounting version |
| Channels: | Input channel: 3 x mono with Mic-Line-Hi.Z. switch via Combination socket (XLR/jack), channel control via rotary dial, 2-band tone control EQ |
| Input channels: | 1 x stereo via RCA or jack plug or Bluetooth, channel control via rotary dial |
| Speaker: | Woofer 8" with ferrit magnet 8 x compression tweeter highs 1.35" with ferrit magnet |
| Type of speaker: | Wireless PA system |
| Carrying handle: | 1 pc/pcs |
| Material: | Plastic |
| Dimensions: | Width: 29 cm Depth: 26.3 cm Height: 39.3 cm |
| Weight: | 8.65 kg |

OMNITRONIC PORTY-8A Bodypack + Lavalier Microphone 863.1 MHz

| | |
|--------------------|-------------------|
| Cable length: | 0.9 m detachable |
| Range: | Range up to 60m |
| Frequency band: | UHF 863 - 865 MHz |
| Carrier frequency: | 863.1 MHz |
| RF power output: | 10 mW |
| Color: | Black |
| Weight: | 0.13 kg |

OMNITRONIC PORTY-8A Transport Bag

| | |
|---------|---------|
| Color: | Black |
| Weight: | 0.65 kg |

Scope of delivery:

1 x OMNITRONIC PORTY-8A Wireless PA System

1 x compact cabinet speaker
1 x microphone
1 x power cord
1 x user manual
1 x declaration of conformity
2 x battery
1 x battery pack

1 x OMNITRONIC PORTY-8A Bodypack + Lavalier Microphone 863.1 MHz

1 x transmitter
1 x microphone
2 x battery

1 x user manual
1 x declaration of conformity

1 x OMNITRONIC PORTY-8A Transport Bag

1 x bag
1 x strap