EUROLITE LED Strip 4in1 Zone RF Receiver

Extension controller with 4 x 6A for RGB/W and dual white

Art. No.: 50531145

GTIN: 4026397659832

The article is no longer in our assortment.

Features:

- Easy paring to the basic kit via remote control
- Any number of controllers possible in 4 zones
- Memory function saves last setting when switching off

  Package contents
- 1 x device, 1 x user manual, 1 x declaration of conformity, 2 x screw

Logistic

EAN / GTIN: 4026397659832

Weight: 0,14 kg

Length: 0.17 m

Width: 0.05 m

Heigth: 0.03 m

Technical specifications:

Power supply:	12/24V DC
Power consumption:	Max. 288 W 12 V DC Max. 576 W 24 V DC 72 W 12 V DC per channal 144 W 24 V DC per channal
Output current:	Max. 4 x 6 A per channal
Power connection:	Via screw terminal
Power output:	Screw terminal
Carrier frequency:	2,4 GHz
Dimensions:	Length: 16 cm Width: 4,6 cm Height: 2,5 cm
Weight:	110 g

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn
All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.