

## EUROLITE LED Confetti Storm

DMX confetti machine with LED illumination and wireless controller

Art. No.: 51707007

GTIN: 4026397625196



### Features:

- Easy-to-use DMX confetti machine with 1300 watts power
- Output nozzle with RGBA LED illumination for impressive effect presentations
- Variable output angle
- Recommended filling quantity for best results: 200-300 g
- Rugged metal housing
- 6 LEDs 8 W SMD 9080 4in1 QCL RGBA (homogenous color mix)
- Color selection; color change adjustable; Dimmer electronic
- Strobe effect
- Output distance: Approx. 5.5 m
- Control via stand-alone; DMX; wireless remote control
- Fixtures available for Light'J; LED PC-Control 512; Light Captain
- For application areas such as: Clubs/dancing school; wedding/gala/events; stage; theater
- Application possibility: Standing

### Logistic

EAN / GTIN: 4026397625196

Weight: 9,30 kg

Length: 0.41 m

Width: 0.30 m

Height: 0.56 m

### Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	1300 W
Power connection:	Fixed power supply cord with safety plug
Lamp type:	LED lamp
LED type:	6 x 8 W SMD 9080 4in1 QCL RGBA (homogenous color mix)

Output distance:	Approx. 5.5 m
DMX channels:	9
DMX input:	1 x 3-pin XLR (M) mounting version 1 x 5-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version 1 x 5-pin XLR (F) mounting version
Control:	Stand-alone; DMX; wireless remote control
Fixtures available for:	Light J; LED PC-Control 512; Light Captain
Carrier frequency:	433.92 MHz
Housing color:	Black
Dimensions:	Width: 24 cm Depth: 30 cm Height: 50 cm
Weight:	8.15 kg
Noise classification:	Class 3 (clearly perceptible sounds)
Battery:	1 x 12 V LR27 alkaline manganese built-in

### **Scope of delivery:**

---

- 1 x device
- 1 x remote control
- 1 x receiver
- 1 x user manual
- 1 x declaration of conformity