

EUROLITE LED PC-Control 512

Lighting control software with USB interface to create professional shows

Art. No.: 51860150

GTIN: 4026397420029



Description:

LED PC-Control is the ideal DMX512 software for all DJ and Architectural applications or small/medium-sized projects. It manages all LED technology-based equipment and can control any type of standard DMX appliance. The software is the most user friendly and affordable solution for DMX lighting control.

Features:

- Graphic and user-friendly live board for touchscreens and smartphones
- Remotely trigger scenes and programs via Wi-Fi with your smartphone or instantly change RGB colors of your LED lights and much more
- Automatic program generator with X-Pan, Y-Tilt and RGB effects
- Graphic patch editor for DMX fixture addressing
- Quick fixture profile editor with 3000 files (libraries) included
- Advanced Matrix editor to allow all LED configurations
- Multiple menu languages (e.g. French, English, German)
- Full RGB (W/A) color and dimmer management and rendering
- Graphic 2D edition of fixtures
- Colors, dimmer, speed, black out and pause can be managed in live mode
- Fade-in time between programs and scenes
- Multiple program triggers
- DMX output speed signal can be configured for perfect DMX line stability and full compatibility with any electronic fixtures (Mab, Break, Delay, frequency 1 to 45 Hz)
- Durable aluminum housing with mounting flange
- Can transmit up to 512 DMX channels
- Control via DMX; SmartBoard DMX App
- The device can be connected via USB to the PC in connection with LED PC-Control 512

Logistic

EAN / GTIN: 4026397420029

Weight: 0,32 kg

Length: 0.20 m

Width: 0.14 m

Height: 0.06 m

- Compatible with Win XP, Win Vista, Win 7, OS X 10.3 or better
- For further information about this product, please refer to the Data Sheet under "Downloads"

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz 5V DC 500 mA
Power consumption:	1 W
Power connection:	Mains input via micro USB (F) mounting version power supply cord for USB A mains connection (provided)
DMX channels:	Output 512
DMX output:	3-pin XLR (F) mounting version
Control:	DMX; SmartBoard DMX App
USB port:	USB 2.0, type mini USB (F) mounting version
Color:	Black
PC connect:	LED PC-Control 512 via USB
Dimensions:	Width: 7 cm Depth: 9 cm Height: 4.5 cm
Weight:	0.22 kg
Operating system:	Win XP, Win Vista, Win 7, OS X 10.3 or better

Scope of delivery:

1 x device
1 x external mains adapter
1 x USB cable
1 x CD
1 x remote control
1 x battery