

EUROLITE LED ML-56 QCL RGBW/RGBA 18x8W si

PRO DMX spotlight with 18 x 8 W 4in1 LED

Art. No.: 51913671

GTIN: 4026397429930



The article is no longer in our assortment.

Features:

- Equipped with 4in1 LEDs in the colors red, green, blue and white and six in the colors red, green, blue and amber
- Through the close chip placement of the multichip technology, an exquisite color blend, even with short distances to the illuminated surface, is guaranteed
- Operable in stand-alone mode or DMX
- Functions: Static colors, RGBAW color blend, color change, color fade, internal programs, dimmer and strobe settings via DMX; Master/Slave
- 3, 5, 7, 8 channel DMX mode selectable
- Sound-control via built-in microphone
- Comfortable addressing and setting via control panel with LED display and three operating buttons
- Easy installation
- Locking possibility at the mounting bracket
- Available in silver or black
- Ready for connection via power cord with safety plug
- DMX512 control possible via any commercial DMX controller
- 18 powerful LEDs 8 W
- Strobe effect
- Control via stand-alone; DMX
- Preprogrammed in Light J; LED PC-Control 512; Light Captain

Logistic

EAN / GTIN: 4026397429930

Weight: 5,00 kg

Length: 0.28 m

Width: 0.27 m

Height: 0.38 m

Technical specifications:

Power supply:

230 V AC, 50 Hz

| | |
|-------------------------|---|
| Power consumption: | 190,00 W |
| IP classification: | IP20 |
| Lamp type: | LED lamp |
| LED: | 18 x 8 W |
| Control: | Stand-alone; DMX |
| Preprogrammed in: | Light´J; LED PC-Control 512; Light Captain |
| Beam angle (1/2 peak): | 18° |
| Housing color: | Silver |
| Dimensions: | Width: 24 cm Depth: 30 cm Height: 31 cm |
| Weight: | 4,60 kg |
| DMX channels: | 3/5/7/8 |
| DMX connection: | 3-pin XLR |
| Sound-control: | via built-in microphone |
| LED type: | 8 W QCL |
| LED number: | 18 |
| Beam angle: | 18° |
| Dimensions (L x W x H): | 240 x 300 x 310 mm |
| Legal specifications | |
| Special product: | Not designed for household room illumination |
| Intended use: | Show effect lighting |