

EUROLITE LED PMB-4 COB RGB 30W Bar NSP

LED color changing bar with narrow beam angle

Art. No.: 51930283

GTIN: 4026397507638



The article is no longer in our assortment.

Features:

- Operable in stand-alone mode or via DMX interface
- DMX512 control possible via any commercial DMX controller (occupies max.16 channels)
- 3, 5, 12 15 or 16 DMX channels selectable for numerous applications
- Supports RDM (Remote Device Management)
- Equipped with 4 x 30 W COB LED in the colors red, green and blue
- Each LED can be controlled individually
- Functions: Static colors, RGB color blend, automatic color change, internal programs, dimmer and strobe settings via DMX, Master/Slave
- Dimmer speed (step response) controllable
- Adjustable white balance
- Sound-control via built-in microphone; sensitivity adjustable
- Comfortable addressing and setting via control panel with LC display and four operating buttons
- Rugged housing and an appealing design
- Ideal as floor spot via base for standing installation
- Locking possibility at the mounting bracket
- Feed-through output allows to power up to 8 devices
- Switch-mode power supply for operation between 100 and 240 Volts
- Power connection via Neutrik PowerCon jack and included power cable with safety plug
- For further information about this product, please refer to the Data Sheet under "Downloads"

Logistic

EAN / GTIN: 4026397507638

Weight: 6,30 kg

Length: 0.51 m

Width: 0.20 m

Height: 0.24 m

Technical specifications:

Power supply: 100-240 V AC, 50/60 Hz

Power consumption: 115,00 W

| | |
|-------------------------|--|
| Dimensions: | Length: 44 cm Depth: 15 cm Height: 16,5 cm |
| DMX channels: | 3/5/12/15/16 |
| DMX connection: | 5-pin and 3-pin XLR |
| Flash-rate: | 18 Hz |
| Sound-control: | via built-in microphone |
| LED number: | 4 |
| LED type: | Array Cluster 30 W, RGB |
| Beam angle: | 15° |
| Dimensions (L x W x H): | 150 x 440 x 165 mm |
| Weight: | 5kg |
| Legal specifications | |
| Special product: | Not designed for household room illumination |
| Intended use: | Show effect lighting |