

EUROLITE DTB-405 4-channel Dimmerbar 5A

Dimmer bar for chaser or DMX operation

Art. No.: 70064420

GTIN: 4026397108057



The article is no longer in our assortment.

Features:

- Makes the installation of your lighting system really easy
 - Installed directly on the stand or crossbeam
 - With 4 spot connections
 - Outputs via 4 safety sockets
 - Can be used either as a 4-channel chaser controller or a DMX dimmer pack
 - 6 different operation modes
 - 16 pre-programmed chaser patterns
 - Chaser direction can be inverted
 - Chaser speed controllable or sound-controlled
 - Sound control via built-in microphone
 - Remote control via optional footswitch
 - Only for professional use
- device**
- Cordless, flexible and versatile
- Package contents**
- 1 x device

Logistic

EAN / GTIN: 4026397108057
Weight: 6,00 kg
Length: 1.35 m
Width: 0.21 m
Height: 0.27 m
Bulky product

Technical specifications:

Power supply:	230 V AC, 50 Hz
Output current:	Max. 5 A per channel
Dimensions:	Width: 1,3 m Depth: 10 cm

	Height: 10,5 cm
Weight:	5,05 kg
Device	
Battery pack type:	1 x nickel metal hydride 3,6 V,
Max. power output:	3680 W
Max. total current:	16 A
Max. output/channel:	1150 W
Max. current/channel:	5 A
Fuse:	F 6.3 A, 250 V
Maximum load per fixation point:	4 kg
Max. spaced braceload:	16 kg
Max. centered braceload:	25 kg
TV spigot:	D = 28 mm
Dimensions (L x W x H):	1300 x 100 x 105 mm