

## EUROLITE DMX Scan Control 192 MK2 Controller

Console for 12 lighting effect units with up to 16 DMX channels, joystick

Art. No.: 70064526

GTIN: 4026397611052



### Features:

- DMX controller for lighting effect units such as moving heads, scanners and LED spot lights
- USB port for storing program data
- Manual, time-controlled or sound-controlled chase running mode
- Fade between scenes adjustable between 0-30 s
- Copy function for scenes and banks
- 2 DMX fixture levels can be controlled
- 8 DMX channel faders
- 1 joystick for precise adjustment of pan/tilt
- Button for fine tuning of pan/tilt
- Blackout function
- MIDI control for banks, chases and blackout
- Can transmit up to 192 DMX channels
- (19") 48.3 cm rack installation 3 U
- Programmable 6 scenes/chases each with max. 240 cues
- Control via DMX; sound to light via microphone; sound to light via RCA (F) mounting version; MIDI via 5-pin DIN (F) mounting version
- Firmware can be updated
- Desktop console housing

### Logistic

EAN / GTIN: 4026397611052

Weight: 2,70 kg

Length: 0.58 m

Width: 0.17 m

Height: 0.13 m

### Technical specifications:

Power supply: 100-240 V AC, 50/60 Hz  
9V DC 800 mA

Pin configuration: Inside + / outside -

|                          |                                                                                                                          |
|--------------------------|--------------------------------------------------------------------------------------------------------------------------|
| Power consumption:       | 10 W                                                                                                                     |
| IP classification:       | IP20                                                                                                                     |
| Protection class:        | Protection class III                                                                                                     |
| Power connection:        | Mains input via coaxial power connector (M) mounting version power supply cord with AC adapter (provided)                |
| Programs:                | Programmable 6 scenes/chases each with max. 240 cues                                                                     |
| DMX channels:            | Output 192                                                                                                               |
| DMX output:              | 1 x 3-pin XLR (F) mounting version                                                                                       |
| Control:                 | DMX; sound to light via microphone; sound to light via RCA (F) mounting version; MIDI via 5-pin DIN (F) mounting version |
| Housing color:           | Black                                                                                                                    |
| Available storage media: | USB devices (FAT 32)                                                                                                     |
| USB port:                | Type A                                                                                                                   |
| Color:                   | Black                                                                                                                    |
| PC connect:              | , firmware can be updated                                                                                                |
| Mounting depth:          | 170 mm                                                                                                                   |
| Housing design:          | (19") 48.3 cm rack installation 3 U<br>Desktop console housing                                                           |
| Dimensions:              | Width: 48.3 cm<br>Depth: 13 cm<br>Height: 8.9 cm                                                                         |
| Weight:                  | 2.30 kg                                                                                                                  |

### Scope of delivery:

1 x controller  
1 x user manual  
1 x external mains adapter