

EUROLITE LCD-12 DMX Dimmer controller

Lighting controller 12 channels

Art. No.: 70064592

GTIN: 4026397119053



The article is no longer in our assortment.

Features:

- Can be used as DMX controller or analog lighting controller
 - 12 channel-faders with LED
 - Fade Time fader with LED for adjusting the step time
 - Master-fader with LED for adjusting the total output level
 - Audio-fader with LED for adjusting the music sensitivity
 - Flash-button per channel and master-flash (Full On-button)
 - LED-display of all modes
 - 0/10 V-output via three 8-pin DIN-sockets
 - 53 built-in programs
 - Dimmer: Manual control of the channels via sliders
 - Full On: all channels can be switched on together
 - Program speed adjustable via speed-fader or Tap Sync-button
 - Sound-control via external signal or integrated microphone
 - External signal connection via RCA socket
 - Power supply via included power unit or via 18-20 V dimmer pack
 - Rack installation
 - Only for professional use
- device**
- Cordless, flexible and versatile
- Package contents**
- 1 x device

Logistic

EAN / GTIN: 4026397119053
Weight: 3,10 kg
Length: 0.56 m
Width: 0.24 m
Height: 0.14 m

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	6,00 W
Dimensions:	Width: 48,3 cm Depth: 13,35 cm Height: 6,5 cm
Device	
Battery pack type:	1 x nickel metal hydride 3,6 V, via 15-18 V DC, 300 mA power unit included in the delivery or optional dimmer-pack
Number of control channels:	12
Integrated programs:	53
Sound-control:	via built-in microphone or via audio-input
Audio-input:	RCA
Audio-sensitivity:	0.1-1 V
DMX512 output:	3-pin XLR connector
Analogue output:	3 x 8-pin DIN-socket
Output voltage:	0/10 V DC
Dimensions (L x W x H):	483 x 132 x 65 mm Rack installation with 3 u
Minimum mounting depth:	90 mm
Weight:	2.6 kg