

EUROLITE KRX-16 DMX lighting controller

DMX lighting controller 16 channels

Art. No.: 70064620

GTIN: 4026397129816



The article is no longer in our assortment.

Features:

- 16 channel-faders with LED
- Fade Time fader with LED for adjusting the step time
- Master-fader with LED for adjusting the total output level
- Audio-fader with LED for adjusting the music sensitivity
- Speed-fader for adjusting the program-speed
- Flash-button per channel and master-flash (Full On-button)
- LED-display of all modes
- 16 freely programmable programs
- Dimmer: Manual control of the channels via sliders
- Full On: all channels can be switched on together
- Program speed adjustable via speed-fader or Tap Sync-button
- Sound-control via external signal or integrated microphone
- Sound to light via RCA socket
- Foot switch connection via 6.3 mm stereo jack plug (1/4")
- Power supply via included power unit
- Rack installation

Logistic

EAN / GTIN: 4026397129816

Weight: 4,65 kg

Length: 0.61 m

Width: 0.32 m

Height: 0.17 m

Technical specifications:

Power supply: 230 V AC, 50 Hz

Power consumption: 10,00 W

Dimensions: Width: 48,3 cm
Depth: 22,5 cm

	Height: 8,9 cm
	via 12-20 V DC, 500 mA power unit included in the delivery
Number of control channels:	16
Integrated programs:	16
Sound-control:	via built-in microphone or via audio-input
Audio-input:	RCA
Audio-sensitivity:	0.1-1 V
DMX512 output:	3-pin XLR connector with polarity selector
Dimensions (L x W x H):	483 x 222 x 85 mm
	Rack installation with 5 u
Minimum mounting depth:	100 mm
Weight:	4.4 kg