

## EUROLITE QuickDMX Wireless Transmitter/Receiver

Wireless DMX system 2.4 GHz

Art. No.: 70064703

GTIN: 4026397532159



**List price: 106.98 €**

incl. 19% VAT.

### Features:

- Auto-switching transceiver
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Can receive and process up to 512 DMX channels
- Can transmit up to 512 DMX channels
- Control via DMX; QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

#### Package contents

- 1 x device, 1 x user manual, 1 x external mains adapter, 1 x uSB cable, 1 x antenna, 1 x declaration of conformity

### Logistic

EAN / GTIN: 4026397532159

Weight: 0,36 kg

Length: 0.14 m

Width: 0.12 m

Height: 0.06 m

### Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz 5 V DC 500 mA
IP classification:	IP20
Power connection:	Mains input via USB C (W) mounting version power supply cord for USB A mains connection (provided)

DMX channels:	Input 512 Output 512
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	DMX; QuickDMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2,4 GHz
Parallel mode:	Max. 6 transmitter
Modulation:	GFSK
Color:	Black
Dimensions:	Width: 21,2 cm Depth: 10 cm Height: 7,5 cm
Weight:	290 g