

EUROLITE DMX AIO Recorder, Merger, Artnet Node, Signal Converter

DMX recorder for 2 universes

Art. No.: 70064835

GTIN: 4026397648362



The article is no longer in our assortment.

Features:

- Wireless DMX recorder and Art-Net node
- Real-time recording and playback of light shows via DMX or Wi-Fi
- Records any Art-Net and DMX source
- Built-in access point
- Art-Net in/out via Wi-Fi or LAN
- 8 memory locations with up to 20 hours recording capacity each
- 2 recording modes: time recording or step-by-step recording
- 2 playback modes: solo run or loop run
- Dimmer and speed fader
- DMX merger (2 in > 1 out) with HTP, LTP, override and backup modes
- DMX splitter (1 in > 2 out)
- Rugged black metal housing
- Can receive and process up to 1024 DMX channels
- Control via DMX; Aurora DMX App; Photon App; Art-NetDmxRemote App
- LCD display
- The device can be connected via USB to the PC

Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity, 1 x power cord, 1 x antenna, 1 x memory card

Logistic

EAN / GTIN: 4026397648362

Weight: 1,41 kg

Length: 0.27 m

Width: 0.24 m

Height: 0.10 m

Technical specifications:

Power supply: 100-240 V AC, 50/60 Hz
Or

	5V DC 500 mA
Power consumption:	4 W
Power connection:	Mains input via P-Con (blue), mounting version power supply cord with safety plug (provided) Mains input via USB C (W) mounting version power supply cord for USB A mains connection (optional)
Power output:	1 x P-Con (gray), mounting version
DMX channels:	Input 1024
DMX input:	2 x 3-pin XLR (M) mounting version
DMX output:	2 x 3-pin XLR (F) mounting version
Network connection:	1x RJ-45 (F) mounting version
Control:	DMX; Aurora DMX App; Photon App; Art- NetDmxRemote App
Display type:	LCD display
USB port:	USB 2.0, type B
PC connect:	Via USB
Dimensions:	Width: 22,7 cm Depth: 13 cm Height: 7 cm
Weight:	1,13 kg