

## OMNITRONIC PA Volume Controller/Program Selector 5W mono wh

Mountable PA program selector and PA volume controller with 24 V emergency priority relay

Art. No.: 80711081

GTIN: 4026397260380



**The article is no longer in our assortment.**

### Features:

- Combination of PA program selector for 6 signal sources and PA volume controller
- Suitable for 100 V audio technique or other signals
- White plastic front panel and knobs
- Built-in 24 V emergency priority relay
- Attenuation in 11 steps
- Screw plug connection
- Flush mounting
- Finery housing (optional)

### Logistic

EAN / GTIN: 4026397260380

Weight: 0,26 kg

Length: 0.17 m

Width: 0.09 m

Height: 0.07 m

### Technical specifications:

Priority relay:	24 V
Power:	Rated: 5W RMS
Frequency range:	50 - 18000 Hz
Input & output:	Mono
Housing design:	Flush mounting Finery housing (optional)
Dimensions:	Width: 8 cm Depth: 6,7 cm Height: 15,4 cm
Weight:	220 g