

## OMNITRONIC PA Vol Contr/Prog Select 20W mono wh

Mountable PA program selector and PA volume controller with 24 V emergency priority relay

Art. No.: 80711083

GTIN: 4026397260601



**The article is no longer in our assortment.**

### Features:

- Combination of PA program selector for 6 signal sources and PA volume controller
- Suitable for 100 V audio technique or other signals
- White plastic front panel and knobs
- Built-in 24 V emergency priority relay
- Attenuation in 11 steps
- Flush mounting in customary 60 mm wall sockets
- Surface mounting with optional PA SF housing
- Mounting depth: 45 mm
- Screw plug connection

### Logistic

EAN / GTIN: 4026397260601

Weight: 0,34 kg

Length: 0.17 m

Width: 0.10 m

Height: 0.07 m

### Technical specifications:

Priority relay:	24 V
Power:	Rated: 20W RMS
Frequency range:	50 - 18000 Hz
Input & output:	Mono
Dimensions:	Width: 8 cm Depth: 6,7 cm Height: 15,4 cm
Weight:	300 g