

## OMNITRONIC TM-1500 Pocket transmitter

Universal multifrequency pocket transmitter

Réf. : 13055512

GTIN: 4026397233452



### Caractéristiques:

- Transmits microphone signals to a receiver with the same carrier frequency
- Operation in the low-interference UHF band (792,500-814000 MHz)
- Up to 8 pocket transmitters with 8 receivers can be operated simultaneously
- Frequency and sensitivity switchable via mini switches
- Can also be used for direct instrument pickup
- 500 carrier frequencies switchable in 50 kHz steps
- Sensitivity can be adjusted continuously
- LCD display with battery capacity and frequency
- Battery capacity transmission to receiver
- Lock function for preventing unintended shutoff
- For 2 x 1.5 V mignon batteries (type AA)
- Operation range 200 meters
- Connection via mini XLR socket
- A lavalier microphone or a headset microphone can be ordered separately
- License-free and approved in Germany
- UHF 792-814 MHz sans inscription et sans frais dans une grande partie de l'Europe

### Logistique

EAN / GTIN: 4026397233452

Poids: 0,42 kg

Longueur: 0.27 m

Largeur: 0.12 m

Hauteur: 0.07 m

### Données techniques:

Type:	Émetteur de poche
Branchement électrique:	Pile/batterie Tramite
Batterie:	2 x 1,5 V AA Mignon LR06 alcaline au manganèse ci-joint

Bande de fréquences:	UHF 792-814 MHz
Sélection de la fréquence:	Fréquence commutable
Commutateur:	Commutateur marche/arrêt
Dimension:	Largeur : 7,5 cm Profondeur : 3,5 cm Hauteur : 11 cm
Poids:	0,17 kg
Channel 61:	792.500-797.900 MHz
Channel 62:	798.100-805.900 MHz
Channel 63:	806.100-813.900 MHz
Modulation:	FM
Frequency stability:	±0,005 %
T.H.D.:	<0.5% at 1 kHz
AF response:	50-18000 Hz
Maximum deviation:	±48000 Hz
RF power output:	10 mW
Coverage:	200 m (with line-of-sight)
Current consumption:	<100 mA @ 3V
Audio input:	Mini XLR
Antenna (L):	105 mm

---

**Contenu de la livraison:**

---