

OMNITRONIC BR-115 Pocket receiver set

Multifrequency pocket receiver set

Réf. : 13062000

GTIN: 4026397139754



Caractéristiques:

- Set includes multifrequency receiver and mini ear phones
- Can be used for in-ear applications
- 16 UHF frequencies (800.100-813.000 MHz) via DIP switches selectable
- LED display for power supply
- Level control
- Audio output via 3.5 mm mono jack socket for mono earphones
- Power supply via 2 x 1.5 V mignon batteries (type AA) (not supplied)
- A wireless microphone or a belt transmitter with lavalier microphone or headset microphone can be ordered separately

Logistique

EAN / GTIN: 4026397139754

Poids: 0,22 kg

Longueur: 0.21 m

Largeur: 0.07 m

Hauteur: 0.06 m

Données techniques:

| | |
|--------------------|---|
| Dimension: | Largeur : 7 cm Profondeur : 2,5 cm Hauteur : 10,6 cm |
| Antenna: | Detachable |
| System: | Non-diversity, one channel |
| Carrier frequency: | UHF 800.100-813.000 MHz (16 ch.) 800.875, 801.375, 802.375, 803.125, 803.875, 804.500, 805.125, 805.875, 806.625, 807.375, 807.875, 808.375, 809.125, 810.250, 810.875, 811.875 MHz |

| | |
|-------------------------|------------------------------|
| Frequency stability: | ±0.005 % |
| T.H.D.: | <1 % at 1 kHz |
| Tone signal: | 32.768 kHz |
| S/N-ratio: | >94 dB at 48 kHz deviation |
| Input sensitivity: | 8 dB |
| Selectivity: | >50 dB |
| Dynamic range: | >96 dB |
| Modulation method: | FM-frequency modulation |
| Coverage: | >30 m (with line-of-sight) |
| Frequency range: | 50-15000 Hz (±3 dB) |
| Audio output: | 3.5 mm mono jack socket |
| Power supply: | 2 mignon batteries (type AA) |
| Current consumption: | approx. 110 mA |
| Battery life: | max. 12 hours |
| Dimensions (L x W x H): | 106 x 70 x 25 mm |
| Weight: | 100 g |

Contenu de la livraison:
