

## OMNITRONIC UA-1000 Antenna distributor

Répartiteur d'antenne

Réf. : 13063020

GTIN: 4026397195347



### Caractéristiques:

- For operating up to four receivers DR-1000 on one pair of multi-antennas
- Replaces the respective antennas and PSUs of the individual receivers
- Up to four antenna distributors UA-1000 can be connected among each other for use of 16 microphones in total
- Low-voltage outputs for supplying four DR-1000, incl. matching connection cables
- Connections for two antenna boosters AB-1000
- All antenna connections via BNC jacks
- Rugged steel housing
- Included in the delivery: 9 BNC connection cables, 2 BNC extension adapters, 4 x 12 V connection cables, 2 rubber antennas

### Logistique

EAN / GTIN: 4026397195347

Poids: 4,05 kg

Longueur: 0.56 m

Largeur: 0.33 m

Hauteur: 0.09 m

### Données techniques:

Alimentation électrique:	100-240 V CA, 50/60 Hz
Puissance totale de raccordement:	100,00 W
Plage de fréquence:	470000000 - 870000000 Hz
Dimension:	Largeur : 48,3 cm Profondeur : 25 cm Hauteur : 4,45 cm
RF output level:	-0.5 dB to 3 dB
Impedance:	50 ohms

Antenna connectors:	2 x BNC
Receiver outputs:	8 x BNC
Low-voltage outputs:	4 x 12-18 V DC
Dimensions:	482 x 250 x 44 mm
	Rack installation with 1 U
Weight:	2 kg

**Contenu de la livraison:**

---