

## Audience Blender 4xPAR-36 QCL LED bk

LED Audience Blender with PAR-36 Blinder housing with RGBW LEDs (4in1)

Réf. : 42103479

GTIN: 4026397443035



**L'article n'est plus disponible.**

## Audience Blender 4xPAR-36 QCL LED bk

LED Audience Blender with PAR-36 Blinder housing with RGBW LEDs (4in1)

Réf. : 42103479

GTIN: 4026397443035

### Caractéristiques:

- Equipped with 24 x 8 W QCLs (quadcolor LEDs) distributed in 4 segments
- Each segment can be controlled individually via DMX
- Sound-control via built-in microphone; sensitivity adjustable
- Functions: Static colors, RGBW color mixture, internal programs, dimmer and strobe settings via DMX, Master/Slave
- 4, 6 or 19 DMX channels selectable for numerous applications
- DMX-controlled operation or stand-alone operation with Master/Slave function
- For use on stages, catwalks, crossbeam systems, or decoration
- Swivelable lamp rows
- Rugged housing and an appealing design
- Comfortable addressing and setting via control panel with LCD display and four operating buttons
- Locking possibility at the mounting bracket
- DMX control via every standard DMX controller