

FUTURELIGHT EASY-4 Remote control

Simple remote control

Réf. : 51834014

GTIN: 4026397263374



L'article n'est plus disponible.

Caractéristiques:

- Suitable for FUTURELIGHT DJ-LED CY-100, FUTURELIGHT DJ-LED Scan 100, FUTURELIGHT DJ-LED CF-100
- For controlling the blackout in Stand Alone-mode
- For switching the gobos and the Auto/Manual mode. In Auto Mode, the gobos are switched sound-controlled. In Manual Mode, the gobos are switched via remote control
- 10 m connection cable with stereo jack
- Commandé via Télécommande câblée

Logistique

EAN / GTIN: 4026397263374

Poids: 0,39 kg

Longueur: 0.20 m

Largeur: 0.17 m

Hauteur: 0.03 m

Données techniques:

Type de protection:	IP20
Commande:	Télécommande câblée
Couleur:	Noir
Poids:	380 g