


Récepteur DMX sans fil WDR-G4 PCB

Récepteur sans fil DMX pour transmission de données sans fil 2,4 Ghz

Réf. : 51834021

GTIN: 4026397656688



Récepteur DMX sans fil WDR-G4 PCB

Récepteur sans fil DMX pour transmission de données sans fil 2,4 Ghz

Réf. : 51834021

GTIN: 4026397656688

Caractéristiques:

- Compact wireless DMX receiver for the wireless transmission of up to 512 DMX channels
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Only for Futurelight products with appropriate installation feature
- Due to AFHSS (Automatic Frequency Hopping Spread Spectrum) and TDMA (Time Division Multiple Access) technology, interference-free operation also alongside other WDR-G4 receivers and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- Operating range up to 200 m (with line-of-sight)
- Simultaneous operation of up to 16 transmitters, thus control of 8192 DMX channels (16 DMX universes) possible
- 1 to 512 receivers WDR-G4 can be controlled by each transmitter
- 2.4 GHz - license-free worldwide
- Peut recevoir et traiter jusqu'à 512 canaux DMX
- Peut envoyer jusqu'à 512 canaux DMX