

FUTURELIGHT DJ-LED CF-100 Matrix effect

LED effect projector with RGB patterns

Réf. : 51837505

GTIN: 4026397263435



L'article n'est plus disponible.

Description:

The flower effect is a real club classic. The beams of the DJ-LED CF-100 are comparable to a laser, but there is no mirror to deflect the beams however and so they are static. But as the mirror in lasers causes a power loss of the radiation, the light of this flower spot is even brighter. Together with smoke, the beams show their brilliant nature.

Caractéristiques:

- Creates 16 various RGB patterns (gobos) via LED matrix
- Gobo rotation
- Strobe effect with adjustable speed
- Equipped with 40 LEDs: 16 x red, 12 x blue, 12 x green
- Long LED life
- Manual focus
- 6.3 mm jack socket for remote control
- Fuzzy sound control: program continues automatically during periods without music or bass-beat
- DMX-controlled operation or stand-alone operation with Master/Slave function (up to 4 slaves)
- Blackout, Gobos and Auto/Manual Mode applicable in Stand Alone mode via optional FUTURELIGHT Easy-4 remote control
- Sound-controlled via built-in microphone
- Control board with 4-digit display
- Advantages of LED technology: long life, low power consumption, minimal heat emission, defacto maintenance free with brilliant light radiation
- DMX control via every standard DMX controller

Logistique

EAN / GTIN: 4026397263435

Poids: 2,85 kg

Longueur: 0.30 m

Largeur: 0.27 m

Hauteur: 0.22 m

Données techniques:

Alimentation électrique:	230 V AC, 50 Hz
Puissance totale de raccordement:	10,00 W
Dimension:	Largeur : 22 cm Profondeur : 21 cm Hauteur : 20,5 cm
DMX channels:	3
DMX connection:	3-pin XLR
Sound-control:	via built-in microphone
Flash-rate:	18 Hz
LED number:	40
Dimensions (L x W x H):	220 x 210 x 205 mm
Weight:	2.4 kg
Spécifications juridiques	
Produit spécial:	Non destiné à l'éclairage de la pièce dans les ménages
Utilisation:	Éclairage pour effets de spectacle