

EUROLITE LED PMB-4 COB RGB 30W Bar NSP

LED color changing bar with narrow beam angle

Réf. : 51930283

GTIN: 4026397507638



L'article n'est plus disponible.

Caractéristiques:

- Operable in stand-alone mode or via DMX interface
- DMX512 control possible via any commercial DMX controller (occupies max.16 channels)
- 3, 5, 12 15 or 16 DMX channels selectable for numerous applications
- Supports RDM (Remote Device Management)
- Equipped with 4 x 30 W COB LED in the colors red, green and blue
- Each LED can be controlled individually
- Functions: Static colors, RGB color blend, automatic color change, internal programs, dimmer and strobe settings via DMX, Master/Slave
- Dimmer speed (step response) controllable
- Adjustable white balance
- Sound-control via built-in microphone; sensitivity adjustable
- Comfortable addressing and setting via control panel with LC display and four operating buttons
- Rugged housing and an appealing design
- Ideal as floor spot via base for standing installation
- Locking possibility at the mounting bracket
- Feed-through output allows to power up to 8 devices
- Switch-mode power supply for operation between 100 and 240 Volts
- Power connection via Neutrik PowerCon jack and included power cable with safety plug
- Vous trouverez de plus amples informations sur ce produit dans la rubrique « Téléchargements » de la fiche technique

Logistique

EAN / GTIN: 4026397507638

Poids: 6,30 kg

Longueur: 0.51 m

Largeur: 0.20 m

Hauteur: 0.24 m

Données techniques:

Alimentation électrique: 100-240 V CA, 50/60 Hz

Puissance totale de raccordement:	115,00 W
Dimension:	Longueur : 44 cm Profondeur : 15 cm Hauteur : 16,5 cm
DMX channels:	3/5/12/15/16
DMX connection:	5-pin and 3-pin XLR
Flash-rate:	18 Hz
Sound-control:	via built-in microphone
LED number:	4
LED type:	Array Cluster 30 W, RGB
Beam angle:	15°
Dimensions (L x W x H):	150 x 440 x 165 mm
Weight:	5kg
Spécifications juridiques	
Produit spécial:	Non destiné à l'éclairage de la pièce dans les ménages
Utilisation:	Éclairage pour effets de spectacle