

## EUROLITE LED PSI-1 DMX Controller

DMX controller for LED luminaries

Réf. : 51930449

GTIN: 4026397277326



**L'article n'est plus disponible.**

### Caractéristiques:

- Up to 12 luminaires can be used with one EUROLITE PSI-1 DMX Controller
- Power 12 x 12 V DC x 2.2 A
- DMX-controlled operation or stand-alone operation with Master/Slave function and Sound-control mode
- DMX control via every standard DMX controller
- DMX address selectable via the control board
- 5, 9, 13, 17, 25, or 49 DMX channels selectable for various applications
- Programmable color-change speed, strobe effect, and fade time
- RGB color-mixing
- 14 internal programs
- Ready for connection with safety-plug
- For wall mounting
- For use with the following luminaire: EUROLITE LED Ball 30 TCL

### Logistique

EAN / GTIN: 4026397277326

Poids: 5,20 kg

Longueur: 0.50 m

Largeur: 0.34 m

Hauteur: 0.14 m

### Données techniques:

Alimentation électrique: 100-240 V CA, 50/60 Hz

Dimension: Largeur : 46,5 cm  
Profondeur : 9 cm  
Hauteur : 27 cm

Poids: 4,80 kg

Max. power: 350 W

Max. current:	1.5 A
Output voltage:	12 V DC
Max. output/channel:	27 W
Max. current/channel:	2.2 A
Number of control channels:	49
Integrated programs:	14
Fuse:	F 4 A, 230 V
DMX output:	3-pin female XLR socket
DMX input:	3-pin male XLR socket
Dimensions (L x W x H):	465 x 270 x 90 mm