

EUROLITE Chaser 405 IEC 4 channels 5A

Chaser controller

Réf. : 70062625

GTIN: 4026397184853



L'article n'est plus disponible.

Caractéristiques:

- 4 channels
- Connection via 4 IEC output sockets
- 16 built-in programs
- Full on: all channels can be switched on together
- Program speed adjustable
- Sound-controlled via integrated microphone or external signal
- Sound-to-light via 6.3 mm mono jack plug
- Audio sensitivity adjustable
- Rack installation

Logistique

EAN / GTIN: 4026397184853

Poids: 2,25 kg

Longueur: 0.54 m

Largeur: 0.12 m

Hauteur: 0.22 m

Données techniques:

Dimension:	Largeur : 48,3 cm Profondeur : 16,3 cm Hauteur : 4,45 cm
Power supply:	230 V AC, 50 Hz
Max. power output:	3680 W
Max. current:	16 A
Number of control channels:	4
Max. output/channel:	1150 W
Max. current/channel:	5 A

Integrated programs:	16
Sound-control:	via built-in microphone or via audio-input
Audio-input:	6.3 mm mono jack plug (1/4")
Audio-sensitivity:	0.1-1 V
Output sockets:	4 IEC sockets
Fuse:	4 x F 6.3 A, 250 V
Dimensions (W x D x H):	482 x 163 x 44 mm
	Rack installation with 1 u
Minimum mounting depth:	220 mm