

EUROLITE DTB-405 4-channel Dimmerbar 5A

Dimmer bar for chaser or DMX operation

Réf. : 70064420

GTIN: 4026397108057



L'article n'est plus disponible.

Caractéristiques:

- Makes the installation of your lighting system really easy
- Installed directly on the stand or crossbeam
- With 4 spot connections
- Outputs via 4 safety sockets
- Can be used either as a 4-channel chaser controller or a DMX dimmer pack
- 6 different operation modes
- 16 pre-programmed chaser patterns
- Chaser direction can be inverted
- Chaser speed controllable or sound-controlled
- Sound control via built-in microphone
- Remote control via optional footswitch
- Only for professional use

Appareil

- Sans fil, flexible et polyvalent

L'étendue des fournitures

- 1 x appareil

Logistique

EAN / GTIN: 4026397108057

Poids: 6,00 kg

Longueur: 1.35 m

Largeur: 0.21 m

Hauteur: 0.27 m

Article encombrant

Données techniques:

Alimentation électrique: 230 V AC, 50 Hz

Courant de sortie: Max. 5 A par canal

Dimension: Largeur : 1,3 m
Profondeur : 10 cm

Hauteur : 10,5 cm

Poids:	5,05 kg
Appareil	
Type de batterie:	1 x Nickel hydrure métallique 3,6 V,
Max. power output:	3680 W
Max. total current:	16 A
Max. output/channel:	1150 W
Max. current/channel:	5 A
Fuse:	F 6.3 A, 250 V
Maximum load per fixation point:	4 kg
Max. spaced braceload:	16 kg
Max. centered braceload:	25 kg
TV spigot:	D = 28 mm
Dimensions (L x W x H):	1300 x 100 x 105 mm
