

## OMNITRONIC RS-802 Recording mixer

Well-structured 8-channel studio and live mixer

Art.n.: 10040075

GTIN: 4026397183245



### Features :

- Low-noise 8-channel mic/line mixer
- 4 mono inputs with XLR sockets, +48V phantom power and balanced line inputs
- 2 stereo inputs with balanced 6.3 mm jack sockets
- Stereo inputs can also be operated mono
- 3-band EQ for all inputs
- Peak LED per mono input
- Aux Send per channel for controlling external effectors
- Stereo Aux Return with balanced 6.3 mm jack sockets
- Separate Main Mix, Booth and headphones outputs
- Tape inputs assignable to Master, Booth/headphones
- Precise 10-fold stereo LED meter

### Logistica

EAN / GTIN: 4026397183245

Peso : 3,25 kg

Lunghezza : 0.37 m

Larghezza : 0.31 m

Altezza : 0.12 m

### Dati tecnici :

Potenza totale installata:	15,00 W
Misure:	Larghezza: 27 cm Profondità: 25 cm Altezza: 5,5 cm
Peso:	2,75 kg
Power supply:	2 x 20 V AC, 50/60 Hz via included power unit
Inputs:	

4 x mono	XLR or balanced 6.3 mm jack
2 x stereo	balanced 6.3 mm jacks
1 x Aux Return:	balanced 6.3 mm jacks
1 x Tape In	stereo RCA
Outputs:	
1 x Master Out	balanced 6.3 mm jacks
1 x Control Room	balanced 6.3 mm jacks
1 x Aux Send:	balanced 6.3 mm jacks
1 x Tape Out	stereo RCA
Frequency range:	
Microphone:	10-60000 Hz, $\pm 3$ dB
Mono:	10-60000 Hz, $\pm 3$ dB
Stereo:	10-55000 Hz, $\pm 3$ dB
Distortion:	0.01 %
S/N ratio:	112 dB
Tone control/channel:	
Treble:	$\pm 15$ dB at 12 kHz
Middle:	$\pm 15$ dB at 2.5 kHz
Bass:	$\pm 15$ dB at 80 Hz
Dimensions (W x D x H):	270 x 250 x 55 mm

**Contenuto della confezione:**

---