

OMNITRONIC HRS-1202 Home recording mixer

Compact 12-channel home-recording mixer

Art.n.: 10040205

GTIN: 4026397262797



Features :

- Low noise 12-channel Mic/Line-mixer
- 4 mono inputs with XLR sockets, switchable +48V Phantom-power and balanced line inputs
- 4 stereo inputs with balanced 6.3 mm jack sockets
- Stereo inputs can also be operated mono
- 3-band EQ for all mono inputs
- FX send control per channel for controlling external effectors
- Peak-LED per input
- Main mix output plus separate phones and stereo CD/tape output
- CD/tape input assignable to main mix or phones output
- 60-mm high-quality faders

Logistica

EAN / GTIN: 4026397262797

Peso : 2,70 kg

Lunghezza : 0.34 m

Larghezza : 0.31 m

Altezza : 0.10 m

Dati tecnici :

| | |
|----------------------------|--|
| Potenza totale installata: | 25,00 W |
| Misure: | Larghezza: 24,5 cm Profondità: 22 cm Altezza: 4,3 cm |
| Peso: | 2,10 kg |
| Power supply: | 2 x 12 V AC, 50 Hz via included power unit |
| Inputs: | |

| | |
|-------------------------|-------------------------|
| 4 mono | XLR |
| 4 stereo | balanced 6.3 mm jacks |
| 1 Tape In | RCA |
| Outputs: | |
| 1 Master-Out | balanced 6.3 mm jacks |
| 1 Aux Send: | balanced 6.3 mm jacks |
| 1 Tape Out | RCA |
| 1 Phones | balanced 6.3 mm jacks |
| 1 Rec | RCA |
| Frequency range: | |
| Microphone: | 10-60000 Hz, ± 3 dB |
| Mono: | 10-60000 Hz, ± 3 dB |
| Stereo: | 10-55000 Hz, ± 3 dB |
| Distortion: | 0.01 % |
| S/N-ratio: | 112 dB |
| Tone control/channel: | |
| Treble: | ± 15 dB at 12 kHz |
| Middle: | ± 15 dB at 2.5 kHz |
| Bass: | ± 15 dB at 80 Hz |
| Dimensions (W x D x H): | 245 x 220 x 43 mm |

Contenuto della confezione:
