

OMNITRONIC LRS-1402ST Live Recording Mixer

Live recording mixer with 14 inputs

Art.n.: 10040229

GTIN: 4026397449143



L'articolo non è più disponibile.

Features :

- 4 mono input channels with gain control, 3-way EQ, low cut and pan control
- 4 stereo input channels with balance control
- Adjustable FX send output
- Inserts for the mono input channels
- Tape input and output
- Separate main mix and control room outputs
- Adjustable headphones output
- Master fader
- +48 V phantom power, can be switched centrally
- Precise 4-digit stereo LED level display
- Operation via supplied power unit

Logistica

EAN / GTIN: 4026397449143

Peso : 2,20 kg

Lunghezza : 0.33 m

Larghezza : 0.29 m

Altezza : 0.09 m

Dati tecnici :

Potenza totale installata:	10,00 W
Intervallo di frequenza:	20 - 20000 Hz
Rapporto segnale-rumore:	>94 dB
Misure:	Larghezza: 22,5 cm Profondità: 24,5 cm Altezza: 5 cm
Peso:	1,80 kg
Power supply:	2 x 18.5 V AC, 350 mA

via supplied PSU

Inputs/sensitivity:

Mic, mono	0.5 mV, combined XLR/6.3 mm jack bal.
Insert	140 mV, 6.3 mm jack unbal.
Line In, stereo	38 mV/150 mV, 6.3 mm jack L/R bal.
Tape In	400 mV, RCA L/R

Outputs/level:

Main Out:	800 mV, 6.3 mm jack L/R unbal.
Control Room	max. 3 V, 6.3 mm jack L/R unbal.
FX Send	max. 10 V, 6.3 mm jack unbal.
Tape Out	60 mV, RCA L/R
Headphones	6.3 mm jack unbal.
Headphones impedance:	>8 ohms
Distortion:	<0.04 %

Tone control/channel:

Treble:	±15 dB at 12 kHz
Middle:	±15 dB at 2.5 kHz
Bass:	±15 dB at 80 Hz
Dimensions (W x D x H):	225 x 245 x 50 mm
