

## OMNITRONIC MRS-1402USB Recording Mixer

Compact audio mixer with 14 inputs and USB interface

Art.n.: 10040273

GTIN: 4026397513905



### Features :

- Built-in USB audio interface allows recordings and playback of digital audio files with a computer (PC and Mac)
- Full duplex USB port: simultaneous recording and playback possible
- 4 mono input channels with gain control, 3-way EQ, Low Cut and pan control
- 4 stereo input channels with 3-way EQ, level switch and balance control
- Adjustable stereo aux send output
- Tape input and output
- Separate main mix and control room outputs
- Headphones output
- +48 V phantom power, can be switched centrally
- Precise 4-digit stereo LED level display
- Operation via supplied power unit
- Rugged, compact metal housing

### Logistica

EAN / GTIN: 4026397513905

Peso : 2,97 kg

Lunghezza : 0.43 m

Larghezza : 0.30 m

Altezza : 0.08 m

### Dati tecnici :

Alimentazione elettrica: 230 V AC, 50 Hz

Potenza totale installata: 28,00 W

Allacciamento elettrico: Alimentazione dell'energia elettrica tramite connettore cavo (M) versione da incasso cavo di alimentazione con alimentatore a spina (in dotazione)

Intervallo di frequenza: 20 - 20000 Hz

Collegamento USB:	USB 2.0, type B
Misure:	Larghezza: 27 cm Profondità: 21,5 cm Altezza: 7,2 cm
Peso:	2,72 kg
Inputs/sensitivity:	
Mic, mono	0.5 mV, XLR bal.
Line In, mono	1 mV, 6.3 mm jack bal.
Line In, stereo	10 mV, 6.3 mm jack L/R
Tape In	100 mV, RCA L/R
Outputs/level:	
Main Out:	650 mV, 6.3 mm jack L/R unbal.
Control Room	2 V max. 6.3 mm jack L/R unbal.
Aux Send:	2 V, 6.3 mm jack unbal.
Tape Out	2 V, RCA L/R
Headphones	2 V, 6.3 mm jack unbal.
Distortion:	0.05 %
S/N ratio:	>74 dB
Tone control/channel:	
Treble:	±15 dB at 12 kHz
Middle:	±15 dB at 2.5 kHz
Bass:	±15 dB at 80 Hz
Phantom power:	+48 V

### Contenuto della confezione:

---